THE MICHIGAN ALUMNUS.

OCT 8 1903

SCIENTIFIC AMERICAN

[Entered at the Post Office of New York, N. Y., as Second Class Matter. Copyright, 1903, by Munn & Co.]

Vol. LXXXVIII.—No. 12. ESTABLISHED 1845. NEW YORK, MARCH 21, 1903. [8 CENTS A COPY $3.00 A YEAR.

Pneumatic Tubes Controlled by One Operator.



Engine and Section of Conduit of the Boston Pneumatic Package Service.



Sending Tubes Connecting With Sales Department. Terminals in Cashier's Office.



Power Plant Showing Engine, Blowers and Main Conduits.



Cashier's Office in a Large Department Store Showing Pneumatic Receivers

THE PNEUMATIC TUBE SYSTEM OF A MODERN DEPARTMENT STORE.—[See page 206].

SCIENTIFIC AMERICAN
ESTABLISHED 1845

MUNN & CO., - - Editors and Proprietors

Published Weekly at
No. 361 Broadway, New York

TERMS TO SUBSCRIBERS

One copy, one year for the United States, Canada, or Mexico $4.00
One copy, one year, to any foreign country, postage prepaid. £0 16s. 5d. 4.00

THE SCIENTIFIC AMERICAN PUBLICATIONS.

Scientific American (Established 1845) ..... $4.00 a year
Scientific American Supplement (Established 1876) ..... 5.00 "
Scientific American Building Monthly (Established 1885) ..... 2.50 "
Scientific American Export Edition (Established 1878) ..... 2.50 "

The combined subscription rates and rates to foreign countries will be furnished upon application.
Remit by postal or express money order, or by bank draft or check.
MUNN & CO., 361 Broadway, New York.

NEW YORK, SATURDAY, MARCH 21, 1903.

The Editor is always glad to receive for examination illustrated articles on subjects of timely interest. If the photographs are *sharp*, the articles *short*, and the facts *authentic*, the contributions will receive special attention. Accepted articles will be paid for at regular space rates.

A 75,000 HORSE POWER TURBINE PLANT.

The great power station which is being erected at Chelsea, London, for the operation of the District Railway system, possesses special interest because of the fact that it will be the first large electrical power station to be operated entirely by steam turbines. The plant will consist of ten turbines, each of 7,500 horse power, with an overload capacity of 50 per cent above the normal rating. The turbines, which are being supplied by the British Westinghouse Company, will be of the Parsons type with Westinghouse modifications. Each turbine will be direct-connected to a three-phase generator of 5,500 kilowatts running at a speed of 1,000 revolutions per minute. There will be only four field-magnet poles, and current will be produced at 11,000 volts potential. The dynamos and the turbines are being built, part of them at the works of the American Westinghouse Company at Pittsburg, and part at the new works of the British company at Manchester. As a result of the high speed of revolution, and the consequent small number of field magnet poles required, the dynamos will be only about 9 feet in diameter; whereas, if reciprocating engines, of the type used at the Metropolitan Elevated Company's power station in this city, were used, running at 75 revolutions per minute, the diameter of the generators would have to be not less than 32 feet.

PERMANENCE OF STEEL FRAMEWORK IN TALL BUILDINGS.

The construction of the Rapid Transit Subway has necessitated the pulling down of a twelve-story skeleton steel building at the corner of Broadway and Forty-second Street, which was erected early in 1899. Its removal has given an opportunity to determine how far the methods adopted for the prevention of rusting or oxidation of the steel of these buildings are successful. Of course, the period of time during which the steel has been incased, three years, is very limited; but it is sufficiently lengthy to afford at least some indications of what may take place during the lapse of centuries. At the time of erection the steel work was given two coats of paint composed of carbon and linseed oil. The columns and girders were incased either in rectangular shells of brick, or with red brick and terra cotta; if with the latter, the spaces between the inclosing material and the steel work were filled in with brick and cement mortar. After the recent removal of the brickwork and terra cotta, the steel was found to be in first-class condition and showed no signs of decay. In the few spots where there was a slight evidence of oxidation, the rust had been on the columns, apparently, at the time they were put up, or it was due to some abrasion of the protecting coat of paint. It is interesting to note that the outside columns supporting the outer walls of the building were found to be in just as good shape as those in the interior of the building. Although, as we have said, the period of test was a brief one, it is considered by architects to have been long enough to establish the thoroughly reliable nature of the standard methods of protection adopted in this form of building.

THE CHANGES IN THE CROTON DAM.

It was to be expected that when the present Chief Engineer of the Aqueduct Commission proposed to make a radical change in the plans of the partly completed Croton Dam, his action would provoke more or less criticism. The vast importance of this great work, the standing and acknowledged professional ability of the former engineer, Mr. Fteley, who is responsible for the original design of the dam, and the fact that the radical changes proposed would involve the tearing down of a considerable portion of the completed structure, combined to produce a feeling of astonishment that any such fundamental reconstruction should now be proposed. However, after giving careful consideration to the reasons assigned for the proposed changes, and making a personal investigation at the dam, the SCIENTIFIC AMERICAN came to the conclusion that so far from having needlessly delayed the completion of the Croton Dam, Mr. Hill, the chief engineer, has not only added greatly to the stability and appearance of the structure, but has prevented the incorporation of a feature in the design which, in all likelihood, would have brought about the ultimate collapse of the dam. To say the least, it was a delicate task to propose a change which would look like an indirect censure of the plans of a distinguished predecessor; and it was a daring task when such changes were certain to provoke a storm of angry opposition from the citizens, who had already grown weary of the prolonged delay in the completion of this much-needed work. While we question altogether the judgment, we can fully understand that it was the best of motives which prompted the Merchants' Association of New York to criticise both the present Chief Engineer of the Aqueduct Commissioners and the Commissioners themselves for the delay of the dam. At the same time it is distinctly fortunate that the present Mayor of New York was able to take a clear grasp of the situation, and so far from removing the Commissioners, as the Merchants' Association demanded, did not hesitate to indorse their work, especially as concerns the proposed changes.

Mr. Fteley, who designed the original structure, substituted an earth dam for a solid masonry dam on the southern end of the structure, for reasons of economy. That he himself was at one time sensible to the risks which led his successor to condemn the earth dam, is shown by the following extract from a report on the great Quaker Bridge Dam, for which the present dam was afterward substituted, made by him as Consulting Engineer to the Aqueduct Commissioners, as far back as July 25, 1887, in which he says:

"An earth dam, with a core of masonry, was also considered. In such structures, the thrusts exerted by the earth against the center wall, during construction and at the different stages of the water surface, when filling or emptying the adjacent basin, are unknown or, at the best, very uncertain; if the wall became fractured under their action, or allowed the water, in places, to pass through, the leaks, under such a considerable and unusual pressure, would endanger the stability of the earth embankment. Moreover, the authorities agree that this kind of structure is not safe to adopt beyond a certain limit of height; and it was thought unwise to attempt an experiment, which owing to the importance of the interests involved, was not justified by the saving in expense which might have been effected by its adoption.

"In this case, where the welfare of New York is concerned, and where the consequences of a possible disaster, with 30,000,000,000 gallons of water behind the dam, may well be imagined, we must deal with certainties; we have before us many successful instances of masonry dams, although of less magnitude, and the proposed structure can be so proportioned and constructed in masonry as to stand effectually the great pressure to which it is to be subjected."

It was in practically the same terms that the present Chief Engineer of the Commission recommended that a revision of the Croton Dam plans be made, to the extent of substituting masonry for earth, and we think that the above quotation from a report of the original designer of the dam itself should silence forever all criticisms that might suggest that the change in the plans was made from any other motive than that of securing the most durable and perfect structure possible.

WARSHIP CONSTRUCTION IN PRIVATE AND GOVERNMENT SHIPYARDS.

BY OUR LONDON CORRESPONDENT.

In view of the experiments of the British Admiralty department, now in progress, to ascertain whether a private shipyard can build warships with greater speed than the government shipbuilding yards, the results in this direction in other countries afford interesting comparisons. In Germany and France battleship construction in both the private and state yards is very and unnecessarily protracted. And this delay constitutes a grave national danger which, it would seem, the respective governments do not adequately appreciate. In England, where, on the other hand, such work is carried out with all possible expedition, it has now become an axiom that "Great Britain can afford to wait until the Admiralty know the designs and efficiency of the projected vessels of other (European) nations before she commences to build a new vessel to excel them." In the case of the German battleship "Kaiser Karl der Grosse," a vessel 377 feet 4 inches in length and of 11,500 tons displacement, with four 9.4-inch guns and eighteen 5.9-inch guns, and with engines of 13,000 i. h. p., capable of developing a speed of 18 knots, she was erected in the private shipyard of Messrs. Blohm & Voss at Hamburg, and no less than 40 months and 5 days elapsed from the laying of the keel until delivered to the government. Even the Krupp firm, notwithstanding its modern and extensive equipment, are not much faster, since they occupied 35 months in building the "Zaehringen." With respect to the Imperial dockyards, they are quite as slow, since it was nearly four years before the "Wittelsbach," a similar vessel to the "Kaiser Karl der Grosse," was ready for sea. In France a similar state of affairs exists, but in this case the delay is more attributable to the uncertainty and hesitancy of the Naval Department, since the French government have a peculiar way of suddenly stopping work upon the construction of one vessel and directing operations upon another ship. But in the case of the three new battleships "Democratie," "Justice," and "Verité," which are each to be of 18,000 horse power, it is calculated that they will occupy four years in building. What is the result of this protracted construction? These three French battleships are of tremendous power, but progress in naval affairs and armaments is so rapid that by the time they are in commission they will be somewhat out of date.

In considering the practice in England, we find that although the government is comparaively slow in construction, everything is being done by the Admiralty to decrease the time occupied in building. The private shipyards, when they have a vessel in hand, crowd the workmen upon it, and get it off the ways as quickly as possible. The recent cases of the Chilean battleships "Libertad" and "Constitucion," and the new type of torpedo destroyer "Erne," offer striking examples of the speed with which battleship construction is carried out. The two first named, notwithstanding their large dimensions and displacement, were launched 10 months after the signing of the contracts, while the builders actually undertook to have the vessels complete and ready for use within 18 months; and if the speed of building with which they were commenced had been maintained, the contract time would have been shortened by one month. To build and equip a first-class modern battleship such as these Chilean war vessels, ready for action, within 17 months is a commendable achievement. In the instance of the torpedo boat destroyer "Erne," a record in quick construction was accomplished. This vessel was launched 7 months after the signing of the contract, and will be handed over to the English Admiralty 6 months below the contract time. Even in the government dockyards quick construction is the chief desideratum, though in this case the speed is not so great as in the private shipyards. But the English Admiralty are determined to cut down the time for building to the minimum, and they have now inaugurated a new system of decentralization, by which there is a superintendent for naval contracts. Speed in construction is the continual demand of the government, and it is furthermore a great national demand. For the battleship costing $5,000,000 upward, when launched, to be out of date, owing to the long time occupied in its construction, is a result which, in the interest of the citizens and the defenses of any country, should be remedied at all costs

"SHAMROCK III."

BY OUR GLASGOW CORRESPONDENT.

It seems to be inevitable that the building of yachts intended for "America" Cup racing should be attended, year by year, by the circulation of a crop of extraordinary stories regarding the appearance of the yachts, and the wonders which they may be expected to perform. The building of the boats now under construction has run to the usual accompaniment, and the British yacht has received, if anything, the larger share of the attention of the resourceful inventors of these rumors. Anyone who has been led by these stories to the expectation of some sensational development in the boat built at Dumbarton to carry Sir Thomas Lipton's third "America" Cup challenge, may be counted foredoomed to disappointment, for the yacht which has been evolved by Mr. William Fife, Jr., differs so little from recent challengers and defenders that it requires the trained eye of a practical yachtsman to identify the developments.

Such changes of type as have been made are, however, none the less important because they are unsensational. In the recent contests which have been sailed for this much-coveted trophy there has been a marked leveling of the abilities of the opposing yachts, and it has come to be recognized on both sides of the Atlantic that a runaway victory for either side is not among the things which can fairly be expected. The last contest, that sailed between Columbia and the Watson challenger, "Shamrock II.," was admitted on all hands to be the closest match ever made for Cup honors, and it would therefore have been rash policy for Designer Fife, when called upon to produce another Cup racer, to have ignored the developments already made and to have struck out in the direction of experiments of unknown value. This consideration should, of itself, have been sufficient to discount most of the rumors regarding the sensational developments to be expected in the Scottish boat.

As a matter of fact the designer of "Shamrock III."

recognized the coming match as one in which the victory is likely to be gained by seconds and minutes, and the boat which he has produced shows that his line of action has been in recognizing and strengthening the weaknesses of the two previous challengers rather than in striving after a marked degree of originality. Generally speaking, it may be said that the chief novelty in the design of "Shamrock III.," lies in the fact that stiffness and great sail-carrying power, which have been the characteristic of each Cup challenger since and including "Valkyrie III.," have been treated on this occasion as a matter of secondary importance. All yacht designing is largely a matter of compromise. If a stiff, powerful boat is the main object of the designer, then the soft flow of the lines which give ease of driving must be sacrificed to some extent. In "Valkyrie III.," "Shamrock I.," and in less degree, in "Shamrock II.," the design was controlled by a desire to produce such a hull as would stand up well to the immense pyramid of canvas which it was proposed to use for driving. In the latest boat the controlling feature of the design has been altered, and Fife has apparently directed his energies first to the posed to use for driving. In the latest boats the conditions of weather. He has therefore given "Shamrock III." a round fullness of body which makes her stand out from the list of challengers as a yacht of marked individuality. The fin-keel type of underbody is naturally retained, but the hull of the boat is drawn so well down that the fin is made much shallower than usual. It is, in short, less of a fin and more of a keel than has been seen on any Cup racer in recent years. The draught has also been cut down to a considerable extent, and the new craft will float in two feet of water less than was necessary to keep the Watson boat off the bottom.

These changes mean naturally a certain loss of initial stability, and to partly compensate for this the beam, as compared with that of "Shamrock II.," has been slightly increased. The full round head which was characteristic of the Watson boat—and helped greatly to her undoing when she met a head sea—has no place in the Fife model. From the point of greatest beam the bow is carried forward in an easy sweep which gives an entrance cleaner than on any of the previous "Shamrocks." The excessive thinning down of the flanks, which was also a noticeable feature of the previous challenger, has also been avoided, and the beam of the boat is carried well out into the counter. In profile the yacht has fewer peculiarities. The bow is shorter and sharper than usual, and rises at an angle that should keep the decks moderately free from water in anything less than a heavy sea. The sheer is peculiar, and looks ungraceful to eyes accustomed to the low waist and the rise fore and aft to which yachts are usually sheered. The rail of "Shamrock III." is practically level.

In the construction of the boat Messrs. Denny Brothers have produced an interesting bit of work, but the interest lies mainly in the details and the quality of the workmanship rather than in the introduction of any new principles. In the matter of material, the boat might be regarded as a retrogression, for the manganese bronze with which the last Cup yacht was plated is discarded in this instance for nickel-steel, such as is largely used in the construction of launches and torpedo boats. The builders, on whose advice this was done, are, however, convinced that this is a step in the right direction. The difficulty of working the manganese bronze and the extra thickness necessary to make up for the doubtful hold of the seams, etc., more than compensated, in their opinion, for the superior smoothness and other advantageous qualities of the alloy. The present yacht is plated from keel to rail with nickel-steel. The plating used in closing in the underbody, where a little extra weight is of little account, is fairly stout, but from the waterline up, where every pound tells against the stability of the boat, the plating is so thin that it is difficult to understand how a satisfactory bedding has been got for the countersunk heads of the rivets. The only aluminium used in the vessel has been put into the decks, whose plates are composed of an alloy which is mainly this light, but perishable metal. Taken as a whole, and allowing for the weight saved by the use of thinner metals, the shell of the boat is lighter than that of "Shamrock II." and works out at a figure very close to that of the first Fife challenger.

In a yacht of this type the spars are always deserving of special attention, as much from their great size as from the ingenuity displayed in the effort to secure the maximum of strength and rigidity with the minimum of weight. In this, Fife had the experience of the last challenger to guide him, and he has made few departures of note. The mast, gaff, and boom are of steel, the bowsprit being solid wood, and the lighter spars of hollow wood. The mast follows the idea carried out in the second spar of this kind fitted to "Shamrock II.," in being mainmast and topmast in one unbroken length. The reason for this is the saving of weight and windage as compared with the ordinary main and topmast, and the saving of weight and complication of gear as compared with the Herreshoff system of telescoping spars. All the steel spars are constructed on the same principle, a framework of light angle steel being first laid down, and bound and strengthened by a series of short straps zigzagging across the diameter of the spar. The complete skeleton is then closed by light steel sheets bent to shape and riveted.

On this occasion there has been abundance of time for the performance of the work; every detail was subjected to searching inspection, and the result is a boat that, whatever her sailing qualities may prove, should at least have none of the weaknesses which helped to mar the career of the second "Shamrock."

THE SECOND EAST RIVER RAPID TRANSIT TUNNEL TO BROOKLYN.

Plans recently submitted to the Rapid Transit Commission by their Chief Engineer for the improvement of traveling facilities in Brooklyn include the construction of a second East River tunnel from Nassau and Orange Streets, Brooklyn, to Maiden Lane, in Manhattan. The tunnel will terminate at a station near William Street, from which point two lines will be run, one across Manhattan to West Street at the foot of Cortlandt Street, and another line below William Street and diagonally beneath the Brooklyn Bridge structure to Park Row, whence it will proceed by way of Center and Grand Streets, to the Manhattan terminus of the Williamsburg Bridge. Here connection will be made between the subway tracks and the tracks which pass over the bridge. It will be seen that this second line will provide a loop for the Brooklyn railways by way of the new tunnel and the Williamsburg Bridge.

Mr. Parsons also recommends removing the elevated trains from the Brooklyn Bridge, sending them across the East River by the new route, and transferring the trolley cars from the roadways to the bridge railroad tracks, thereby restoring the roadways to the exclusive use of vehicles. It is also proposed to connect the two bridges by adding two tracks to the Second Avenue Railroad, and building a new branch of the elevated system down Delancey Street to the Williamsburg Bridge. If these suggestions are carried out, Brooklyn and Manhattan will be connected by three bridges carrying six elevated tracks and ten surface tracks, and by two tunnels carrying four tracks. The report also recommends for Brooklyn a new subway system and a development of the elevated railroad system. From Flatbush and Atlantic Avenues the terminus of the tunnel now under construction, it is proposed to build a four-track subway to the Prospect Park plaza, with a loop at the plaza, and from this loop to carry a three-track line easterly below Eastern Parkway and East New York. Another proposed extension is to run from Flatbush and Atlantic Avenues below Fourth Avenue to Fort Hamilton. In addition to these extensions of the subway system, the report proposes no less than nine new elevated lines or extensions of existing elevated lines. The cost of these improvements exclusive of abuttal damages will be about $52,000,000; $31,000,000 being for the subway system and $21,000,000 for the elevated system extensions.

SPICES—PURE AND OTHERWISE.

BY A. S. ATKINSON, M.D.

Spices properly used have their value in helping digestion and stimulating the flow of the gastric and pancreatic juices, and at the same time they tempt the jaded appetite to a better relish of good, wholesome foods. But spices are not always what they are sold for; neither are they always as wholesome and harmless as they should be. The tendency to adulterate extends to nearly all our foods, and unfortunately a good many people in buying cheap foods are not getting all they bargained for.

When adulterations are wholesome or harmless, possibly the deception is not so bad, especially if we cannot distinguish by taste the genuine from the artificial. Naturally dealers and manufacturers in adulterated foods try to select harmless articles to mix with their adulterated goods. Whatever the nature of the material used for adulterating, it is always cheaper than the genuine goods. It is usually some woody substance, which when ground fine enough will pass muster without being easily detected. Thus in such spices as cloves, cinnamon, mace, allspice, nutmeg, mustard, and ginger, there are many such materials as ground cornmeal, parched wheat, peas, beans, and coffee beans, which can easily be mixed with them without changing the general appearance or even taste beyond lessening the strength. As some people like chicory in their coffee, so some people might prefer adulterated ginger and mustard to the full strength of the genuine article. If the adulteration is to be done, however, it is much more desirable that it should be done at home than in the store.

Ginger, for instance, is frequently adulterated with pepper, mustard hulls, and turmeric. These give nearly as sharp a taste to the mixture as pure ginger would, and the effect is that the adulterated spice frequently passes unchallenged. Cinnamon has quite a variety of materials used for cheapening its retail cost. Cassia, arrowroot, mustard hulls, charcoal, burnt shells and cracker dust are all frequently ground to swell the bulk of the spice. Then in cloves we have some of these same materials, and such other articles as clove stems and hulls ground up, allspice, peas, wheat, and even mineral colors. Nutmegs, since the days of the first Yankee nutmegs made in Connecticut of white birch colored to resemble the natural ones, have been susceptible to considerable adulteration, and starch, cereals, mustard, peas, and other roasted articles go to make up ground nutmegs. Of course, whole nutmegs are hard to imitate, but even these are sometimes sold as genuine when they are nothing but wild, flavorless nutmegs.

Pepper has its weight increased with the addition of such cheap and harmless substances as bran, peas, rice, corn, charcoal, mustard hulls, sago, arrowroot, and cocoanut shells. None of these add any spicy flavor to the combination but they serve to enhance the profits of the maker. If one had the time to separate these different articles of adulteration and examine them carefully through a microscope, he would easily see the deception practised upon him. A good many dealers will tell you that harmless adulteration like this is liked by many people. They prefer the mixtures and blends which they put up, and therefore it does no harm. It is a good deal like coffee and tea blends which dealers mix for their customers, using cheap grades with the high grades, and then selling the results at the highest prices. This may be partly true, but no deception can be practised continually without causing some danger.

For instance, some spices act as a special poison to many people. The mere touch of ginger in one person's food is sufficient to cause nausea and great suffering. Cinnamon to another acts like a mild but quick poison, and mustard in any form will cause another to break out in red, prickling spots. All these spices when mixed together, or adulterated one with another, might be the contributing cause to a person's illness and death. For instance, the person using pepper may be easily affected by mustard, and if the pepper is adulterated with ground mustard hulls the damage is done. Ginger is sometimes mixed with mustard, and the result in using these two together might develop strong symptoms of poisoning.

One cannot afford to take into the system anything under a disguised name. The modern man and woman of intelligence have studied their diet sufficiently to know what disagrees with them, and they do not care to have anything smuggled into their stomachs under some fraudulent name. To many the chances of harm from such a source appear very remote indeed, and they discard them from serious consideration; but to others it is a matter which seems not so slight. It makes a difference whether one is in delicate health or strong and robust in flesh. The former cannot take risks that the latter might daily face in his eating with perfect impunity.

SCIENCE NOTES.

A civil war record of the height of Indiana soldiers shows that out of 118,254 there were 15,047 5 feet, 10 inches tall; 8,706 5 feet, 11 inches; 6,679 6 feet tall; 2,614 6 feet, 1 inch; 1,357 6 feet, 2 inches; 406 6 feet, 3 inches; and 330 over 6 feet, 3 inches. Commenting on these statistics, Dr. Gould, Actuary of the United States Sanitary Commission, writes: "It is evident from our statistics that the Indiana men are the tallest of the natives of the United States, and these latter the tallest of all civilized countries."

Silk is known to be the secretion of two glands of the silkworm alongside of the digestive canal. These glands, which consist of tubes in numerous coils, terminate in the spinning-wart, and open in a common orifice from which the secretion, of the consistency of honey, issues forth, promptly hardening into a thread on exposure to the air. Usually the silk is colorless on leaving the body of the silkworm, but sometimes it is straw yellow or greenish. There has been a dispute of long standing between the savants as regards the origin of this coloration. Some claimed that the larva itself produced the color, others ascribed it to impurities which it acquired upon secretion, and still others were of the opinion that the green color of the leaves of the mulberry tree was the cause of the coloring. The last-named opinion seems to be the correct one. Latterly, Levrat and Conte fed silkworms on mulberry leaves which had been saturated with non-poisonous aniline red and aniline blue. The result was that not only the silkworms turned red or blue, but they also secreted silk of the respective colors. Injections of the above-named dyestuffs into the anal organ of the silkworm produced the same result.—Die Seide.

THE MONTREAL GRAIN ELEVATOR.

In a recent issue we published an article describing the "grasshopper" elevator for the handling of grain in harbors, and especially for raising grain from the holds of vessels and delivering same in any desired locality. We take pleasure now in presenting to our readers one of the most modern and best-equipped storage elevators erected on this continent.

The contract for the elevator was awarded April 16, 1902, by the Harbor Commissioners of Montreal. The design for the elevator was prepared by the Steel Storage and Elevator Construction Company, Buffalo, N. Y., and, before awarding the contract, the plans were submitted to the Minister of Public Works for the Dominion. At his direction, a board of experts examined into the plans very thoroughly and were unanimous in their approval. The time specified for completion of the elevator is August, 1903. The elevator foundations, lower story, and all upper floors are built of concrete. The bins are cylindrical in shape, built of steel plates, with all spaces between cylindrical bins formed into smaller bins, so that the whole area is utilized for storage. The total number of bins is 78; and the total storage capacity, 1,000,000 bushels.

The marine tower is built of steel, and is 23 feet wide, 33 feet long, and 150 feet high; it will be mounted on twenty pairs of car wheels running on four steel rails along the dock.

This dock is now being built by the Steel Storage Company. It consists of a middle section in front of the elevator, which will be built entirely of concrete and steel construction, supported on piles. The width of this section of dock is 33 feet, height 25 feet, and length 200 feet. At either end of the middle section is a heavy concrete retaining wall with filling behind, which will form the dock beyond the elevator. The total length of concrete dock is 600 feet, running across the inshore end of the basin between the two adjacent steamship piers. The total height of the concrete work under the elevator from pile heads to bin bottoms is 50 feet. About 25 feet of this will be below grade when the filling is completed. Two car tracks run through the elevator.

This lower concrete story is thoroughly braced by heavy concrete arches running entirely across the building, with buttresses extending out on either side to take the thrust. The space between columns, as shown on our illustration, will be filled by a concrete curtain wall with a double window, three sashes high, in each panel, which will make a very light lower working floor. The entire outer surface of the concrete will be blocked off to resemble massive masonry, and bush-hammered all over. The top of the bins, as shown in the engraving, will be 110 feet above ground level, and the cupola will run 85 feet above this, making a total height from the ground of 195 feet.

This cupola will be structural steel throughout, with concrete floors and roof. The elevator will be equipped to receive grain either from boats or cars, and ship grain either by cars or by means of conveyors to ocean boats lying at their berths at either King Edward, Alexandria, or Jacques Cartier piers, and at the basins between these piers. The total number of berths served by this elevator will be fifteen. The total length of conveyor to be installed in connection with this elevator for loading ocean boats will be over 9,000 lineal feet.

The handling capacity will be: Receiving grain from boats, 18,000 bushels per hour. Receiving from cars, 20 cars per hour. Shipping to vessels by means of conveyors, 80,000 bushels per hour. Shipping to cars, 48 cars per hour. The elevator is designed so that a second movable tower can be built at any time, with the effect of doubling the receiving capacity from boats, or, in other words, raising it 36,000 bushels per hour. It is the intention to build this extra tower as soon as the business of the port demands it. The elevator, if working only one-third of the time during the navigation season of 150 days, would be capable of receiving and shipping more than 18,000,000 bushels.

The whole building will be thoroughly lighted by incandescent electric lights. The elevator will have a complete dust-collecting and burning system. It will also have an electric passenger elevator, washrooms and office for foreman, and all conveniences to make it complete. The cleaners installed in the elevator will be specially constructed of steel throughout, so as to be absolutely fireproof. All machinery in the elevator and conveyors will be driven by electric motors, and the total horse power represented by these motors, when the conveyor system is complete, will be about 2,500. The current will be furnished by one of the power companies doing business in Montreal. In the elevator will be a transformer station and switch room for controlling all the motors.



ERECTING THE MONTREAL STEEL AND CONCRETE GRAIN ELEVATOR.

The World's Inventors.

The Patent Office statistics inform us that the Britons are the most inventive of all foreigners; that for the year 1901, the patents issued to British inventors numbered 999; while the Germans, in spite of the advantages of quieter surroundings, come forward with only 743 inventions. It is granted that the Americans are the leading inventors, and naturally our cousins on the other side are next in line. The Connecticut people are supposed to be the most inventive of all. Benjamin Franklin was a Bostonian, Samuel F. B. Morse and Elias Howe were New Yorkers. George M. Pullman lived in Cook County, Ill. The Maxims are Maine men; Thomas A. Edison comes from Ohio, and the world-frighting Gatling opened his eyes in the South.

Patents tell only a part of the story. They have nothing to say about those wonderful airships (our foremost theorist on air sailing is a Bostonian, Samuel Pierpont Langley) that always go to smash just before whirling around the vast empyrean, or about the still more wonderful perpetual motion machines, or about the yet unattempted desideratum (greatest of all, perhaps)—a machine to rock and sing the baby to sleep. The world is yet at the mercy of infants and nurses. Nor do patents tell of the inventors of gods or goddesses in the East, or of the inventors of romances that publishers will not take a chance with.

As for Connecticut's reputation, however, it will endure forever and brilliantly, if for no other reason than that the prince of Yankee inventors, the Hon. Phineas T. Barnum, author of "The Humbugs of the World," hailed from Bethel and lived to be mayor of Bridgeport and the head of the "Greatest Show on Earth."—Washington Times.

By-product coke ovens are coming more and more into general use, and at nearly all the establishments where they are being utilized, extensions are being made in this particular. In a short time there will be 1,310 of these ovens in use.

BULL'S SELECTIVE SYSTEM OF WIRELESS TELEGRAPHY.

BY A. FREDERICK COLLINS.

Since the recent successful tests in cableless telegraphy have proven beyond the peradventure of a doubt the feasibility of long-distance transmission, greater effort than at any time heretofore has been made to solve the difficult problem of syntonization.

In nearly every system except the one under consideration, syntonic or selective wireless telegraphy has been based on the principles of electrical resonance, in which the resonator is made to respond sympathetically to the emitted waves of the oscillator in virtue of the similarity of their electrical dimensions.

It is easy to show theoretically the action of a syntonic system based upon the parity of the coefficients of the oscillator and of the resonator as exemplified by a given receiver responding to a given transmitter, and it may likewise be shown by actual experiment that the deductions upon which the theory of resonance was evolved are correct.

But in applying these principles practically it has been found that there are other factors which must be reckoned with, and as these are not constant a serious obstacle is at once brought prominently into evidence. As an illustration of the foregoing statement, in a practical system of wireless telegraphy one side of the oscillator and one side of the resonator are connected with the earth; now the earth acts as a capacity, and as such it varies constantly and so changes the whole system connected with it.

To avoid these difficulties Mr. Andres Bull has designed a system which operates mechanically and in which the dimensions of the sending and receiving circuits are not factors controlling the matter of selection, but instead a fixed number rate of wave impulses actuate different receiving instruments in accordance with prearranged time intervals.

The instruments employed in the Bull system of selective wireless telegraphy are shown in the photographs, Figs. 1 and 2. The "disperser" and "collector," as Bull terms the transmitter and receiver, are combined in the apparatus illustrated in Fig. 1, *A*. This mechanism is connected by means of gearing to an electric motor, *B*, the speed of which is controlled by a Siemens & Halske brake regulator, *C*. The device represented by *D* consists of an electro-magnet connected with and automatically controlling the disk referred to. Fig. 2 shows a number of Morse registers connected with the collector or receiving apparatus.

In transmitting a wireless message an ordinary Morse key is employed. When the key is closed the current from the battery, 1, Fig. 3, flows through and energizes the electro-magnet 2. This attracts an armature, to which is attached a clutch, the side elevation being shown in Fig. 4. Attraction of the armature serves to draw the clutch out of engagement with a pin, 4, on the disk, 3, and this permits the disk to rotate by frictional contact with the shaft, 5, at a speed of about five revolutions per second. In the course of each turn of the disk the pin, 3, closes the circuit, of which the battery, 7, and the electro-magnet, 8, form a portion, through the medium of the contact springs, 6.

If it is desired to send a dot the key is made to close the circuit for a period of less than one-fifth of a second, so that the clutch will engage the pin and bring the disk to a stop as soon as it has made one complete revolution. Thus the current flows through the circuit, which includes the magnet, 8, in the form of a single impulse. When it is desired to send a dash the key is held into contact for a sufficient period to permit the disk to revolve several times, when successive current impulses flow through the circuit at intervals of one-fifth of a second. This actuates the transmitter or disperser, consisting of a disk to which are attached four hundred steel springs, 9, positioned vertically near the periphery. The free ends of these springs pass through radial slots (as shown in Fig. 3) in an upper and oppositely disposed disk, 10. These slots permit movement of the springs relative to the disk in a radial line only. The disks are mounted on the same shaft or spindle, which in turn is mounted vertically in the frame of the disperser. The shaft is rotated at the rate of one revolution per second. A brass ring, 11, is secured to the frame and serves as a guide for the spring points, 9, so that when the disk revolves they slide either within a U-shaped groove, 12, formed by the ring or within the ring itself.



Fig. 5.—The Receiver, Showing Connections Between Coherer Relay, Morse Register and Collector.



Fig. 6.—Diagram Showing Impulses of Series and Specimens of Tape.

Referring again to Fig. 3, a bronze arc, 13, whose ends conform to the angle described by the dotted lines, *a*, is inserted in place of the brass ring at that section. The bronze piece, 13, has a projection extending toward the concentrically arranged springs, and causes these springs in traversing this section to bend toward the polar projection of the magnet, 14, which then attracts them, being constantly energized by a current from the battery, 7. Thus attracted, the springs slide along the projection until the edge, 15, is reached, when they are released and instantly spring back into their normal position. As the disks continue to revolve, the steel springs simply slide within the ring, 11. This is the normal process which takes place when the magnet, 8, is not energized; but if the electro-magnet, 8, is excited the armature to which the finger, 16, is attached will be swung forward so that it projects slightly in front of the polar projection of the magnet, 14. When this occurs the springs in clearing the finger, 16, are forced from the pole of the magnet, 14, when they will again assume their vertical position in virtue of their elasticity and will pass into the U-shaped groove at 17, remaining there until the disk has completed its cycle.

The purpose of this device is to establish contact at certain prescribed intervals with the induction coil, 20, and the oscillator which emits the electric waves. This is done by means of a number of contact points, 18, fitted to the circumference of the frame supporting the disperser; these consist of two contact springs insulated from each other; when the steel springs, 9, move within the ring, 11, they just clear the contact springs, but when passing in the U-shaped groove, 12,



Fig. 2.—The Receiving Station.



Fig. 4.—Sectional View of Disperser.



Fig. 3.—The Transmitter, Showing Connections Between Disperser and Induction Coil.



Fig. 1.—Main Apparatus of the Bull System of Selective Wireless Telegraphy.

THE BULL SELECTIVE SYSTEM OF WIRELESS TELEGRAPHY.

they project sufficiently to make contact and therefore close the circuit operating the induction coil.

If the magnet, 8, is not excited and the disk is revolved the steel springs will slide within the ring and all the contact points will be open; if on the other hand the key is closed and a current impulse is sent through the magnet, the steel springs sliding through the groove make connection with each of the contact points in passing them. The electrical connections between the steel springs and the contact points and the induction coil and oscillator system is clearly shown by the dotted lines and it is evident that upon contact being established between a steel spring and the points the circuit will be closed and the current from the battery, 19, will operate the magnetic circuit closer, 20, thus causing the current from the battery, 21, to flow through the primary of the induction coil, 22, when a disruptive discharge takes place through the spark gap and electric waves are emitted. Now for every current impulse that flows through the disperser magnet, 8, by means of the key, 1, a series of electric waves are radiated, which equal the number of contact points, 18, and since the disks revolve at approximately constant speed the time intervals between a series of impulses will be proportional to the angular distances between the contact points, and thus by varying the distance between these points and by arranging these at different positions around the frame of the disperser the series of impulses or waves may be varied at will and within wide limits. When the electric waves thus emitted impinge upon the receiving antenna (Fig 5) the normally high resistance of the coherer is instantly lowered and the local current flowing through the coherer and relay magnets, 23, actuates its armature, closing an auxiliary circuit in which is included the decoherer, 24, for tapping the filings back to their normal resistivity, and the collector magnet, 25, which is in shunt with the tapper. The collector, as the receiving mechanism is termed, is constructed on the same principles as the disperser, Fig. 3, in fact they may be substituted one for the other by means of proper cut-outs. It will therefore be clear that for each series of impinging waves a steel spring is brought into the groove of the ring, 26. The disk of the collector, to which the steel springs are attached, revolves at a speed isochronous, practically, with that of the disk of the disperser; hence the angular distances between the springs brought into the groove will be proportional to the time constant between the series of electric waves received by the antenna; e. g., if five electric wave series are transmitted, five springs will be brought into the groove of the collector at angular intervals representing the intervals of time between the series of waves. The points, 27, making contact in the collector are arranged in the same relative positions as they are in the disperser, the springs moving in the groove forming the controlling contacts; these are connected in series with the Morse register, 28, and consequently contact is made by all the points simultaneously. Now when the mutual angular value is the same for the points and the springs a prearranged series of electric waves will bring the latter into the groove, and as the disk revolves the series of steel springs, corresponding to the series of waves, will make contact simultaneously at all points; the battery current operating the Morse register then flows through the circuit and prints a dot on the tape. A succession of wave series will produce a dash, or a row of dots reading as a dash. Wave series of any other combination than those to which the collector is adjusted will not operate the Morse register, for simultaneous contact is not possible and the circuit is left open.

In the experiments conducted by Mr. Bull only one transmitter and one receiver were employed, but the disperser was provided with three sets of contact points, 27, and was so arranged that any set desired could be operated by the induction coil, by means of a switch, and thus any one of three series of waves could be emitted and received at will. Uniformly with the diperser the collector was equipped with three sets of similarly arranged contact points, each set being connected with a Morse register, enabling the operators to use any one of three combinations to the exclusion of all others. Three series or combinations of waves only were required, as shown diagrammatically by S^1, S^2, and S^3, Fig. 6 *A*. The element of time is represented by the horizontal line and the wave series or combinations by the vertical heavy strokes; the equi-distant spaces marked by the vertical lines designate 0.05 of a second. At *B*, Fig. 6, is illustrated how the wave series are registered rhythmically when the key is kept closed. By this arrangement selective wireless messages were sent and received with accuracy and dispatch and were printed in Morse characters on the tape of that register only for which it was intended, the other two machines remaining inoperative. Specimens of the tape from the three registers are shown at I., II., III., Fig. 6, each of the three series, S^1, S^2, and S^3, being employed successively. The speed attained approximated fifty letters per minute.

This is the first time in the history of wireless telegraphy that three messages have been transmitted and received simultaneously and selectively and it is also the first time in the history of the art that mechanical methods have been successfully employed in obtaining selectivity. The sending and receiving instruments may be set up at different points and at varying distances, which is a decided advantage over those systems based on pure electrical resonance.

THE PNEUMATIC TUBE SYSTEM OF A MODERN DEPARTMENT STORE.

BY DAY ALLEN WILLEY.

The use of pneumatic tubes in transmitting money, papers, and parcels of various kinds has become so extensive that the service is considered a necessity in the equipment of the modern mercantile establishment. The plan is not a new one. Improvements, however, which have been made in the system in the last two or three years have greatly increased its practical value. In the dry goods or department store, for example, it is valuable as a labor saver, dispensing, as it does, with the many cash boys, in some instances cash girls, that have been employed, and performing their work much more quickly, besides avoiding many mistakes which formerly occurred. There is no delay in "making change," as the amount due the customer is usually handed him by the salesman within a minute, sometimes less than a minute, after his money has been taken over the counter. The system also assists in checking or auditing the sales, for the charge or cash slip which represents the amount of the transaction is sent to the cashier or bookkeeper, where it is examined and verified before being returned.

In the ordinary store the pneumatic tubes extend from the cashier's and bookkeeper's departments to the principal sales departments, varying, of course, in number according to the extent of the establishment. Each tube is termed a "line" and is usually 2¼ inches in diameter. The tubes are generally extended along the ceiling or under the floors for the purpose of economizing space, and the terminals where the carriers are received and sent are of various shapes adjusted to suit the conditions. The system is so laid out that when a sale is made the clerk prepares his purchase check, gets the money from the purchaser, and places it in a small brass cylinder which can be unscrewed at the end merely by a twist of the fingers. To start the carrier, it is necessary only to insert it in the receiving end. The air forces it through the line to what is called the main station. This is usually in the cashier's office, for so many articles in the retail store are sold for cash that no entry is required. The carrier drops into the open receiver at the end of the tube, from which it is taken by the "change maker," who, as already stated, glances over the figures on the slip and verifies the total. If an error has been made, the slip and money are returned to the department from which they were sent. If correct, the slip is returned with the amount due the customer. If the sale is to be charged, the slip of course contains the name of the customer in addition to a description of the article and the amount due. As soon as it has been examined, the clerk in the cashier's office again places it in the carrier and inserts it in the tube or line connected with the bookkeeper's department. Here the memorandum is taken out, entered on the books, and either the original slip or a duplicate is returned to the salesman.

These operations are usually performed in less time than it takes to read the description; for the carrier travels at a rate varying from 1,000 to 2,500 feet per minute, according to the air current. The length of a line is seldom over 600 feet. The current is produced by the blower system, and the mechanical plant installed provides for a force representing from one-fourth to one-half horse power to each line, depending upon the number of bends or curves and the amount of service. A store having a "50-line" service therefore requires an engine of about twenty-five horse power. In some systems the blowers are operated by steam power direct, but electric motors, either direct connected or bolted to the blowers, are preferred.

The air current is maintained in the tube system in the following manner: The various lines are connected with what may be called a main conduit, which leads to the engine room and to the blowers. These blowers draw the air from the various sending terminals of the line, expelling it through a conduit of suitable size, which may open in the engine room or be connected with the street. While the velocity of the current varies according to the speed of the blower fans, the minimum is rarely less than 2,500 feet per minute, the pressure in the tubes ranging from 6 to 12 ounces per square inch, the latter pressure being secured with a service of one-half horse power. The principle is simply the exhaustion of the air in the tubes to produce a partial vacuum. The effect is so powerful that, although the carriers and their contents weigh a half pound, they are transported without difficulty. The suction is not apparent twelve inches from the end of the receiver. Consequently, the end of the receiver can be placed over a desk or table on which light material, such as paper or currency, is spread. Incidentally the system is of considerable value from a hygienic standpoint, as it assists in the ventilation by continually changing the air in the apartment where the terminals are installed.

The carriers are merely cylinders of sheet brass covered at each end with felt to protect the metal from abrasion in passing around the elbows of the tube. They range from four to six inches in length for the ordinary store service, but do not fit closely against the side of the tube. Enough space is provided to allow the carrier to be borne along by the air current with little or no friction except at the turns, thereby permitting of a much greater speed than if the carrier acted as a piston and was continually in contact with the tubing. The receiving terminals are of two kinds, although both work automatically. The ones used in the cashier's and bookkeeper's department are merely open tubes, which are usually suspended over a receiving table or desk. An air valve is placed in the receiver at a point three or four feet from its end. This is so adjusted that merely the pressure of the carrier against it opens the valve. The carrier then drops by gravity to the end of the receiver, and is taken out by the cashier's clerk or bookkeeper. As soon as the carrier passes, the valve is shut by a spring, and thus the current is confined. The air is then diverted into a parallel tube connected with the sending terminal, the operation of which has already been described. The return tube to the sales department also terminates in the valve, which is located directly at its mouth. When the carrier is sent back, its impact is sufficient to open this valve, and it drops upon the salesman's table, the valve closing automatically and confining the air current as in the other instances. The system in the cashier's and bookkeeper's department requires some one to take the carriers out, in order that they may be examined as they are received, thus preventing unnecessary delay in making change. As the extent of the service is limited only by the power of the blower plant, some of the pneumatic systems which have been installed in department stores recently constructed are very extensive. Perhaps the largest in the United States is located in Philadelphia. It consists of over 250 stations, each connected with a line varying from 400 to 500 feet in length. A plant of 150 horse power is utilized, and in all nearly 20 miles of tubes are used. The power is sufficient to force the carriers through every line as rapidly as they can be inserted in the tubes.

Carriers of three and four inches in diameter are employed for transmitting papers and small packages in factories and warehouses, where bulkier material is required to be transferred from one portion to the other. The arrangement of the tubes is the same, and the carriers are received and dispatched according to the same plan, the power plant being of course, correspondingly larger to meet the requirements.

Not only the blower, but the compressed air system is utilized in the long-distance tube service which is employed by the government in New York and other large cities in connection with the Post Office Department. Thus far the plants for transmitting mail have been principally used in conveying it between New York and Brooklyn by way of the present Brooklyn Bridge and between the main post office in New York and the Grand Central Station. Here carriers which are 10 inches in diameter and about 3 feet in length are employed. The most extensive installation of this kind, however, is in operation in Boston, extending from the retail shopping district on Harrison Avenue to Back Bay, South End, Roxbury, Dorchester, and other sub-stations. This system conveys carriers which are 10 inches in diameter. The tube is laid underground, and consists of ordinary cast-iron water pipe finished at the joints in order to make a close fit. It is laid like a water conduit, with lead and iron joints, the curves being of 12 feet radius to the center line. The bends were cast in sections, the standard of 90 degrees comprising three 30-degree sections bolted together. The carriers which, as might be imagined, were manufactured especially for the purpose, consist of sheet metal riveted together, but move through the tube on wheels, five of which are placed at each head. The carrier is opened at the side by a hinged door. On account of size and weight, the terminals are of special design. The receiving terminal consists of an air cushion closed at one end by a revolving valve, opened and closed by a cylinder and piston operated by the air from the tube. Ordinarily this valve is closed, but when a carrier enters the receiver, it compresses the air in front of it. This pressure affects a small auxiliary valve. When the carrier is brought nearly to rest, the auxiliary overbalances and moves the controlling valve of the main cylinder. This opens the revolving valve, and allows the carrier to roll out. Just at the end of the receiver two vanes are mounted, so that the pressure of the air behind the carrier tends to move them. This motion is made

use of to restore the auxiliary valve to normal position and close the receiver. The carrier is placed in the tube by moving valves connected with an air lock.

The power for this system, which is over ten miles in length, is compressed air, the service requiring about 1,400 cubic feet per minute, the pressure varying from 1¾ pounds to 2 pounds. Before entering the compressors the air passes through a tank filled with calcium chloride, which effectually removes all moisture. This tank is open to the atmosphere, and the pipe connections are so arranged that the air of the incoming line passes through the tank and returns to the compressor. Only such air has to be dried as is lost through leakage or used for operating the machines. The compressors are duplex belt-driven with 21-inch x 12-inch cylinders. There are two each at the main, South End, and Roxbury stations, and one each at Dorchester and Back Bay. The compressors are driven by 50 horse power, three-phase induction motors of the internal resistance type.

The system has been found to be an excellent substitute for wagons and other methods of delivery, and is largely used by merchants for sending parcels to the residence districts where sub-stations are located. At these they are sorted and distributed to the houses of the customers by teams and messengers. It is found that the average time required to deliver packages from the main station to any portion reached by the service is ten minutes, where from forty-five minutes to an hour would be required by the usual method of delivery.

The pneumatic postal tube system of New York city has been fully described and illustrated in the columns of the SCIENTIFIC AMERICAN.

Correspondence.

Interest in the Jane Naval War Game.

To the Editor of the SCIENTIFIC AMERICAN:

I beg to congratulate you on your energy and enterprise in securing the right to publish the series of Jane's Naval War Game. You not only deserve credit for supplying your readers with such an intensely interesting subject, but you deserve credit for drawing the attention of the nation to a critical state of affairs.

It is true we may never go to war with one of the powerful European nations; but the best way to make sure of that is to have a fleet that they would dread to encounter. Owing to our late "expansion," we now need two fleets; one in the Atlantic second only to England's, and one of considerable power in the Pacific.

The "War Game" shows how greatly we would have to weaken our Atlantic fleet if an attack should be made on the Philippines—and there is where it would be made—as far as possible from our home base of supplies.

If civilians are allowed to join the new Naval League I would like to have the honor of becoming a member. Can you kindly give me any information about that? I have been looking for some professional criticism of the "Battle of Manila." There seem to be some lessons of great importance in that engagement; though I think the Americans were not given credit enough for gun fire and probable skill in action. One of the lessons is—modernize the "Oregon" class by substituting 12-inch guns for the 13-inch, lowering the 8-inch turrets so the guns can fire on a line with the keel, and using the weight saved by adding more 6-inch guns. All 13-inch guns ought to be replaced by 12-inch. Some "semi-battleships" carrying two or four 10-inch guns and not less than twenty 6-inch guns would make a welcome addition to meet such vessels as the "Kaiser" class. B. D. MERCHANT.

San Jose, Cal., March 5, 1903.

Safety of Railway Travel in England.

To the Editor of the SCIENTIFIC AMERICAN:

The awful accidents which one hears of almost daily in this country would be comparatively few if the railroads were operated on the same basis as those of England. There is not a railway in England that is not fitted out with a complete block signaling system, which is worked by an army of trained men, most of whom enter the railway service as boys at fifteen and sixteen years of age, and usually start in the signal boxes or cabins as telegraph learners. They serve two, three, and even four years, until they are thoroughly acquainted with the telegraph instrument and the working of the signal box, when they are drafted out as relieving signalmen, and are appointed signalmen whenever a vacancy arises. A man when once appointed to a box usually holds the same position for quite a number of years, so that he is able to get thoroughly conversant with everything around him. He has to have good eyesight and hearing, being examined for this about every two years. The signals and points mostly all work together by means of an interlocking arrangement, so that when the switch or point is pulled the signal is pulled at the same time. Nearly every country station has its signal cabin or box with signalmen always on duty. These usually have twelve-hour shifts, but in busy yards they work on eight-hour shifts. On single-line roads, or what are termed "branch lines," they work by what is called the "train tablet system." With this system it is impossible for two trains to be at the same time in one section. The train tablet is worked by an electrical arrangement from one signal box to the other, and the enginemen of the trains before starting on their journeys on a single road are compelled, under penalty of instant dismissal, to see that they have the train tablet handed to them by a responsible person and fixed in a secure position on the footplate, where they can see it. When they reach the next section they have to deliver one tablet and receive another. Trains running in an opposite direction they pass at stations booked in their time table book, or, if trains are running late, arrangements are made accordingly; so that under this system it is almost impossible for a collision to occur. In nearly every branch of the railway service a man has to start at the bottom and be trained up to the more responsible positions; but at busy times when traffic is heavy, most railways employ supernumeraries to do less important duties. The hours of enginemen and firemen are not to exceed ten to twelve hours on duty, so that there is no chance of their being overworked. The officers of the various departments have to draw up weekly reports of hours worked by railway servants and these are sent in to the Board of Trade authorities.

Now as to the keeping up of the roadbeds, bridges, culverts, etc. There are district engineers appointed for so many miles of road, which is divided up into so many sections. Each section is kept in good working order by five men, the foreman, platelayer or "ganger," as he is termed, and four men to work under him. One of the ganger's most important duties is to traverse the entire length of his section every day to see that everything is all right and to report any serious defect in the road or bridges, etc., to his district engineer, who then informs the heads of the various departments, who issue out printed forms to all persons concerned, so that they can be on the lookout and be prepared to stop if required to do so. On nearly every railway there is a man to about every mile of road, so that it gives them a good chance to keep the road in thorough repair. Should a collision or railway accident of any kind occur, there is a Board of Trade investigation, presided over by Major Marinden or Colonel York, to determine the cause and the persons responsible for it. The very few accidents that take place around London, where the traffic is so thick, especially at Waterloo Station, during the Derby, Ascot, and Kempton Park race days, when trains are arriving and departing every minute or so, is truly remarkable, particularly since London is subject to heavy fogs. These, however, they are always prepared for, by having the platelayers do their part as ground signalmen to lay the detonators or torpedoes when required, so as to warn enginemen when they cannot see the signals, etc.

Now as to the important duties of the enginemen. The engineer is supposed to keep a strict lookout for all signals, and the fireman is to assist him in doing the same when not engaged in firing up or putting water in the boiler, etc. The rules require firemen to do these duties as far as possible between stations, especially on express trains, and to be on the lookout for signals on approaching stations and junctions, so that if the engineer did not catch sight of the signals the fireman would, especially when traveling by night. Then again there are issued, every three months, time table books for the drivers and firemen. At the head of each leaf of the book the following is printed: "Time must not be made up in running down inclines, and the men are supposed not to take any chances whatever." When an engineman is leaving a station with his train he is supposed to look back and see that the entire train is following and be prepared to stop if signaled to do so. All these things go toward making the safety of the traveling public complete as shown by the fact that not a single life was lost on British roads last year. ALFRED T. LANCASHIRE.

Little Valley, N. Y., March 7, 1903.

A Coal Substitute.

To the Editor of the SCIENTIFIC AMERICAN:

As a coal famine is subject to occur in the future, possibly the following regarding cheap fuel might be of use to the public in districts where the material is found to exist.

While living in South Wales we used to send to a neighboring pit for a horse load of slack coal, costing 60 cents. This we mixed with two-thirds clay (dug up near the house) in the form of mortar, and then turned it out by hand into balls three or four inches in diameter. These, when dry or nearly so, we placed on already started coal fires for heating rooms, coal at the time being extremely cheap and handier for cooking. They became like balls of red-hot iron, giving out great heat and lasting about twenty-four hours, when they crumbled to ashes. The fire was renewed by placing more on top and making a fuel, as may be seen, costing only 20 cents the ton.

Now it occurs to me this peculiar clay (no doubt some vegetable substance) must exist in many parts of the North American continent, probably in large quantities, possibly beneath the entire prairies, among mountains, beneath some kind of swamps, and overlying coal fields. Also that it can be made to burn by a mixture with some other material, such as sawdust, peat, or finely chopped straw or cornstalks.

For those living inconvenient distances from coal mines or wanting cheap fuel, I would suggest experimenting with any kind of clay they think might have these properties. It will cost little time or trouble. It would be easy for the government to import one or two hundred pounds from the same spot for analysis. To any one communicating direct I will give such further information as lies in my power.

HENRY TAYLOR.

Chaworth, London South, Ontario, February 14, 1903.

The Designing of the "Connecticut."

To the Editor of the SCIENTIFIC AMERICAN:

In view of the fact that the General Board of the Navy has unanimously advised Congress to have our future battleships follow the lines of the "Connecticut" class, it would be interesting to examine this design and see if advantageous changes are possible. The design for the "Connecticut" is probably the finest piece of work of its kind that has ever been turned out here or abroad and the action of the English Admiralty in discarding completely their own previous designs, and practically copying the "Connecticut" for their latest and largest battleships, is a great compliment to our designers.

In looking first at the armament of this battleship, it shows up both enormously powerful and excellently proportioned; nevertheless it looks like a mistake to reduce the length of her 8-inch guns from 45 to 40 calibers, and 100 rounds per 7-inch rapid-fire gun does not seem sufficient.

The writer thinks that these two items should be changed, even if it should be necessary to omit two or even four of the 3-inch guns and their ammunition supply. This could be done without materially impairing the fighting efficiency.

In regard to the protection, the results do not appear to be quite so satisfactory. The larger part of the side is covered with 6-inch armor only; and in view of the fact that foreign navies are increasing the sizes of their broadside guns, and that the thickness of the casemate armor on the latest designs in England is 9 inches and 7 inches, this is too light.

It would be possible, by slightly modifying the plans, to carry a casemate belt of 7½-inch uniform thickness extending from the main belt to the main deck, with athwartship armor of the same thickness by proceeding as follows:

Stop the lower casemate belt at the same point that the upper stops at now, and carry the lower athwartship armor across to meet the barbettes just under the upper. This will result in a saving in length of both the lower casemate and lower athwartship belt, and on one side of the ship would amount to about 545 square feet of 6-inch armor, equivalent to 3,275 square feet of 1-inch armor.

Next dispense entirely with the 2-inch nickel steel protection to the 3-inch guns; battle experience having shown this class of armor to be dangerous, it not being sufficiently thick to exclude common shell from guns of 6 inches and above, and would only serve to make the explosion of such shells more disastrous. This would save about 700 square feet of 2-inch armor or 1,400 square feet of 1-inch, making a total saving of 4,675 square feet of 1-inch armor.

To increase the thickness of the casemate and athwartship belts to a uniform 7½ inches, would require about 2,420 square feet of 1½-inch armor and 1,630 square feet of ½ inch, equivalent to 4,450 square feet of 1-inch armor.

This process would leave a margin of 225 square feet of 1-inch armor for each broadside, and for the whole ship would save about 8 tons in weight.

The barbettes would have to be changed to meet the above conditions, making the face outside of the 7½-inch armor 10 inches thick, and the portion inside 6 inches thick.

This would involve a very slight increase in weight, which could be deducted from the surplus 8 tons.

The proposed changes would lower the position of the center of gravity of the masses involved about 5 feet, and would apparently add to the efficiency of the ship.

Note.—The above discussion is based on the plans submitted by Admiral Bowles to the Society of Naval Architects and Marine Engineers at their last annual meeting. G. B. M.

677 Washington Street, W., Bath, Me., March 2, 1903.

A CURIOUS ELLIPTICAL BRIDGE.

A clever and peculiar example of bridge construction and erection has recently been carried out upon the seacoast of County Antrim in the North of Ireland. At this point the shore drops precipitously into the sea, the cliffs known as "Gobans' Cliffs," which tower to a height of 200 or 300 feet, being of the basaltic origin seen in this part of the country.

This seacoast scenery is of the wildest and withal most beautiful in its solemn grandeur in the North of Ireland; and to enable visitors and tourists to view the spectacle from its most advantageous points, and also to gain access to the many remarkable caves in the vicinity, a walk has been cut out and built in the face of the cliffs, which in itself constitutes a commendable engfneering achievement. This pathway is only from two to three feet in width, and winds along the face and climbs the cliffs in a most extraordinary manner, which from a short distance always imparts to the promenade a most perilous appearance, since immediately below, the waves thunder among the rocks. But the walk has been most skillfully and cleverly designed and constructed. Steps are cut roughly and broadly into the solid rock, but to insure perfect safety to climbers a handrail has been provided. The intervals between the rocks are spanned by delicate and spider-looking bridges of iron. The length of the walk so far constructed is nearly three miles, and it is to be continued for another two miles, which it is anticipated will be completed within a few months. The work is being carried out by the Belfast and Northern Counties Railroad under the supervision of Mr. Berkeley Wise, the chief engineer to the railroad.

The most notable triumph of engineering in connection with this work is the erection of what is known as Gobans' Bridge. This structure is distinctive owing to its curious design, being elliptical in shape. This piece of work was rendered necessary to span a gap 65 feet in width, giving access from the mainland to an isolated rock known as "The Man-of-War."

The general shape of the ellipses of the bridge and its method of construction may be comprehensively gathered from our illustrations. The bridge has a clear span of 65 feet, but is 70 feet in length from end to end. The main structure of the bridge consists of twelve ellipses made of steel placed equidistant. The major axis of each elliptical section is 7 feet inside, with a minor inside axis of 4 feet 8 inches. As will be seen from our illustrations, each of the ellipses is made in two segments of 3-inch by 3-inch by ⅜-inch angles. They are spaced 7 feet 3 inches centers, except the end ones, which are 2 feet 4½ inches centers. The ellipses are held firmly in position by means of longitudinal iron bars, attached to the ellipses by means of stiffening plates 10 inches by 10 inches by ⅝-inch. The longitudinal members are angles 3 inches by 3 inches by ⅜-inch, and the flat bars are 3 inches by ½ inch. The ellipses are additionally strengthened by means of diagonal stays or bracings extending from the points where the half sections of the ellipses are joined.

This arrangement yields a stronger foundation to that portion of the ellipse which is to carry the greatest weight, i. e., the floor. The diagonal lattice steel girders are 3 inches by ½ inch, and carriers for floor angles 3 inches by 3 inches by ⅜ inch. The flooring of the bridge comprises two pieces of pitch pine 12 inches in width by 3 inches in thickness, laid upon the interior bottom surface of the ellipse and raised sufficiently therefrom to afford a perfectly flat surface upon which to walk. In the cross section therefore the internal major axis from the floor to the crown of the ellipse is sufficient to afford a clear walking space to accommodate the tallest persons.

Owing to the exposed position of the site of the bridge, the turbulency of the surf playing upon the rocks immediately below, and the strength of the tides, it was found impossible to erect the bridge on the spot. Under these circumstances the structure was erected at Belfast and transferred intact to a scow. The latter was then towed to "The Man-of War" rock and carefully brought to, as far as possible, immediately below the spot where it was to be installed. Lifting tackle was then placed in position upon each side of the gap to be spanned at the roadway level, and the lifting cables attached to each end of the bridge. The hoisting operation had to be carried out with extreme care, owing to the cramped space in which the lifting tackle was operated, and to prevent the structure being thrown by its own swinging motion when suspended in the air against the face of the rocks, which would have seriously damaged it. The structure was, however, lifted to its position without mishap. It was originally intended to stay the bridge when in position with guys, but when the bridge was erected it was found to be sufficiently rigid to dispense with these additional supports. The bridge was designed by Mr. Berkeley Wise, the chief engineer to the Belfast and Northern Counties Railroad of Ireland.

PECULIAR BRIDGE CONSTRUCTION ON THE NORTH COAST OF IRELAND.



GENERAL VIEW SHOWING THE POSITION OF THE BRIDGE ON THE CLIFFS.

Railroad building by electric light is the experiment about to be tried by the Santa Fe Railroad Company, when it begins the construction of its cut-off line which will connect the Pecos Valley line with its main line in New Mexico. A large electrical plant will be installed at the mouth of the Abo Pass Canyon, and six hundred laborers will be kept at work all the time.

Profits of Irrigation in the Eastern Part of the United States.

The rise in prices of agricultural lands in the last few years has made it necessary that farmers should get the largest possible return from their lands, and has created a general interest in whatever will help to that end. One of the aids now being considered is irrigation. In the East it is not, as in the West, absolutely necessary for the raising of any crops, but, like fertilizing or thorough cultivation, is a means of increasing the returns from land. The whole question is whether it will pay. The report of the irrigation investigations of the Department of Agriculture for the year 1901, carried on under the direction of Elwood Mead, gives some valuable data on this question. The report covers experiments in Missouri, Wisconsin, and New Jersey.

A series of experiments extending over several years at the Wisconsin Experiment Station at Madison shows a marked increase in the yields of farm crops. The average increase in the yield of clover hay on irrigated land over that from unirrigated land has been 2.5 tons per acre; the average increase in yield of corn has been 26.95 bushels per acre; and potatoes show a gain of 83.9 bushels per acre. The annual cost of irrigation at Madison has been $6.68 per acre, not including any interest on the investment, but including all extra labor. At current prices, this leaves a net profit from irrigation of about $20 per acre on hay, $11 per acre on corn, and $73 per acre on potatoes. The conditions of soil and climate at Madison do not differ from those of the Middle West generally, and the results given above show that where water can be obtained without too large an outlay irrigation as a part of intensive farming is very profitable.

Another series of experiments was begun for testing the effect of irrigation and fertilization on sandy soils, such as are common in large sections of Michigan, Wisconsin, and Minnesota. These lands are poor in plant food, and retain so little moisture that all attempts to farm them have failed. The experiments included the supplying of both manure and water. Manure alone was of little use, as there was not water enough to make the plant food available. Water alone produced good results, but the application of both gave the best results. The cost of irrigation was $6.70 per acre, and the net gain from irrigation was as follows: Potatoes, $30 per acre; corn, $1 per acre; watermelons, $58 per acre; muskmelons, $45 per acre. From these experiments it seems that with special crops irrigation of the sandy lands is profitable, but the increase in yield of corn is not enough to justify the expense of securing a water supply.

In New Jersey water has been used on small fruits and vegetables, and the added returns due to irrigation vary a great deal with the seasons. Some years no irrigation is needed, in others all crops need it, but in most years some crops are helped by it. Prof. Voorhees, who has charge of this work, reports that in his opinion, irrigation where tried has paid well. Pumping from streams or wells is the most common way of getting water for fruit and garden irrigation. Small plants furnishing water enough for from five to ten acres, including pump and engine, cost from $200 to $500.

Farmers around Butte, Mont., have organized to make a fight against the owners of the ore smelters in that vicinity, which, it is claimed, have ruined the agricultural industry of that section. The statement is made by the farmers that no less than five tons of sulphuric acid and half that amount of arsenic are discharged into the air daily, and that the crops for a great many miles around are affected.

WHERE OLIVES GROW.

BY CHARLES F. HOLDER.

In the wide valley of San Fernando, down by the crumbling mission of San Diego, or in the shadow of the picturesque pile of Santa Barbara, the stroller finds some of the oldest olive groves in California. They were planted by the old padres, inspired by the old and true Italian proverb, "An olive orchard is a gold mine on the face of the earth. He who plants an olive orchard plants for the centuries a perpetual income." Whether it is the associations or the charm of the climate, that is one of eternal summer so far as real winter is concerned, there is a fascination about the olive fruit and tree that induces many to attempt its culture aside from the merely commercial reasons. We see the old grove at San Diego from the mesa on which stands the fast-crumbling mission. It lies in the valley against low hills through which arroyos have broken. Along this old King's Highway are some of the oldest date palms in America, and among them is a modern windmill startling in its incongruity.

There is something particularly attractive about the olive tree; its very shape tells of thrift; its upright growth, graceful and pointed leaves, olive-hued now, but turned by the gentle wind, glisten like silver. It is generally supposed that the home of the tree was in Italy, where it has been known for ages, and where the growth is so slow that it is a common saying that a man plants olives for his grandchildren; but on the foothills near Elizabeth Lake a wild olive has been found, a large and thrifty tree. It appealed to the early Californians because it came into early bearing and practically never died. The old trees of San Fernando, which have been deserted and neglected for seventy-five years, are now being cared for, and are rapidly throwing out branches and assuming their normal shape and beauty, and bid fair to equal the famous trees of Europe and Asia, which have been bearing fruit for one thousand years.

AN OLD MILL AT SAN FRANCISCO.

The enthusiast, if he is the man to succeed, does not come to California to sit in the sun and watch things grow, but comes prepared to concentrate all his intelligence upon the work in hand. The successful culture of the olive, or any other fruit, in California requires intelligence and work as elsewhere, despite the fact that nature invites, indeed urges, one to rest by the wayside.

It is the land of *dolce far niente*, but not to the successful orchardist; he must be a man of vigor and energy and eternal vigilance his watchword. Having secured his land, he buys from some reliable dealer cuttings taken from good, sound trees. These are three-fourths of an inch in diameter and two-thirds of a foot in length—slender material one might think from which to produce a bearing tree in four years. These cuttings have been taken from the parent tree in December or January, and are planted in rows in sandy soil, being replanted permanently in February and March at a distance of about twenty feet apart. These will grow readily, and for a year the ground is kept well turned, the bush then being trimmed into a tree by cutting all the shoots but one, and in succeeding years the grower watches the tree and prunes it, with the idea in view of making a lusty tree. In four years some berries will be obtained, and the orchardist is delighted at the luxuriant growth and the rich green olives, which hang so gracefully, but yet not sufficiently abundant to be of commercial value. In the sixth year the trees should produce thirty gallons each, and in eight years the grower finds himself in possession of a beautiful and productive grove. The trees have grown so wide that they fill the entire space and meet, and each tree under the most favorable conditions should produce forty gallons of olives. The orchardist figures that with one hundred trees to an acre, and forty gallons per tree, he will have four thousand gallons; but there are pests and other enemies which materially reduce this estimate. Indeed, if the grove produces a fourth of this, he is doing well.

In November, when the first rains come, the olives ripen, and as soon as the berries begin to turn purple the picking begins; and if five hundred acres have been planted and are in bearing, a gang of Mexicans

SAN DIEGO MISSION WITH OLIVE ORCHARD AND DATE PALMS.

THE OLD OLIVE MILL AT SAN JUAN CAPISTRANO.

CALIFORNIA OLIVES.

WILD OLIVE TREES AT LANCASTER, CAL.

and others may be seen on the ground. Each picker carries a canvas open bag suspended in front of him, about the neck, and a good picker should pick four hundred pounds per day. Some use ladders; others pick from platforms on the wagons which are driven along. After the picking the olives are subjected to a drying or evaporating process, and now the orchardist is confronted with the most delicate part of his work, the making of olive oil. In the olden days the crusher or mill was a conspicuous feature of every mission, and that of San Fernando is still in good condition, while the ruin of the old mill of San Gabriel is one of the points of interest in the San Gabriel Valley. The temperature of the drier is not over 130 deg., and so arranged that the work is completed in two days. The drier itself has a capacity equal to the production of the grove, that of one orchard being 500 square feet of surface, and holding about 2,000 pounds of olives; five pickers at 400 pounds a day keep it filled. The crusher is interesting. It resembles a millstone, but rests on its edge, which is six inches broad and runs in a circular trough six feet across, made of cement. Its axis is a long pole which is fastened to the center of the trough, at the opposite end of which is harnessed a horse, the motive power; in the old days several Indians performed the work.

In such a mill, seemingly small for the purpose, the product of an orchard of one thousand trees can be crushed. The millstones differ in size, and in large orchards there are several. A building is generally erected over the crusher, and the horse works outside of it, as everything about the olive is kept as clean as possible. The olive pulp is taken from the crusher and massed in lumps or cakes about three feet square and three inches thick. The press resembles a New England cider press, and two are required to press out one hundred gallons of oil a day. The entire process is interesting. The result from the press is run into tanks, where it remains for three months, the oil rising to the surface, where it is readily recovered. The seemingly dry pomace or residuum in the press is put through a second crushing and treated to a bath of hot water, by which a large quantity of second-quality oil is produced, even a third quality being made. The oil now obtained goes to the clarifier or filter, which is a series of boxes from five to seven in number, the bottom covered with fine cotton batting. Some use a series of metal boxes, one in the other, each having a wire sieve bottom, the oil dripping from one to the other, and coming out pure and as beautiful as liquid amber. The majority of foreign or imported oils are adulterated and made up of cottonseed or hog's lard. The extent to which this is carried may be realized from the fact that the cottonseed exportations from New Orleans for this purpose in one year were sufficient to fill fifteen million oil bottles at a cost of ten cents per bottle.

The orchardist probably pickles and bottles a portion of his crop, and in California there is an ever-increasing demand for the ripe olive, which when cured is very dark and rich. In pickling, the olives are first placed in fresh water, which is changed daily for forty or fifty days, after which they are placed in salt brine to be changed several times, and finally placed in a brine the water of which has been boiled, and there are many variations from this which result in the attractive olive of commerce. The orchardist now has a fine producing grove, but his paths are not all *coleur de rose*, as while the olive can be said to be freer from pests than many other trees, yet success is only attained at the price of eternal vigilance. Nature is capricious, and does not always produce conditions perfectly favorable. A year of intense heat may come just at the wrong time, or a cold snap may literally nip the year's prospects in the bud, and early in his experience the orchardist is confronted with an army of pests which he must fight day and night. How discouraging this is at times can be realized by a glance at the authorities on the olive scale insect, by whom we are told that one female will produce four thousand eggs, and that a single coccus will produce five generations, nearly six billion descendants; or at the end of a year, according to Lejourdan, the progeny of a single female will be one billion billion. This is appalling, yet the world's supply of olive oil is kept up, and the pure oil of California leads in quality and return.

A new floating pontoon dock is being constructed in Great Britain for Durban, South Africa, to replace the one which was recently wrecked on the rocks off the coast of Cape Colony, while *en route* from England to its destination. This new dock is to be much more powerful than the one which was wrecked, though it will be similar in construction. It will measure 475 feet over all—an increase of 110 feet over the wrecked dock—while its lifting capacity will be 4,000 tons greater—8,500 tons as compared with 4,500 tons.

Engineering Notes.

The Pennsylvania Railroad has a contract to take all the cars which can be turned out by the Pressed Steel Car Company, between December 1, 1902, and June 1, 1903. The capacity of this plant is one hundred cars per day. This means an expenditure of $15,000,000, and will increase the capacity of the Pennsylvania equipment by about 750,000 tons.

After having been extensively overhauled and renovated, the Hicks Locomotive and Car Works at Chicago Heights, Ill., is now in full operation. The improvements consisted of replacing all the original buildings with a single exception with fine well-lighted and ventilated buildings. This concern is devoted almost exclusively to the repairing and rebuilding of heavy and modern locomotives. The capacity of the works is at present 15 locomotives, 15 coaches and 200 freight cars per month. Thirty locomotives can be handled at one time at the Hicks plant.

In connection with the speed trials of the new British cruiser "Drake," in which a speed of twenty-four knots was obtained while running at full speed, experiments were carried out with a new type of propeller, the blades of which are almost circular in shape, instead of the present approach to the oval form. By this arrangement the screws obtain a more powerful grip of the water. Owing to the conspicuous success which attended the speed trials of the "Drake," since the maximum speed contracted for was only twenty-three knots, it is proposed to carry out further tests with the propeller upon other vessels.

The Pennsylvania Railroad has been experimenting with a new style of track, which has been laid for the purpose of making a practical test on the Fort Wayne Division, at Leetsdale, Pa. The tracks are laid on a pressed-steel girder of trough shape, and directly supporting each rail with channel spacers to maintain the gage and fastenings for the rail, which do not require the use of bolts, wedges, or any other movable parts. This constitutes the rail in its entirety, and although simple in construction, is effective in providing a solid track without the use of heavy ballast, as is required by the wooden ties.

The commission appointed by the French Admiralty to investigate the subject of water-tube boilers, to ascertain the best all-round boiler of this type for naval vessels, and to investigate the respective advantages of small-tube and large-tube boilers, has published its report. The commission recommend the adoption solely of large tubes for boilers fitted to battleships and armored cruisers. Experience has conclusively proved to the commission that the small-tube boiler, while it gives a higher evaporation per square foot of heating surface than the large-tube boiler, consumes far more fuel per unit of power, while it is also more difficult to clean and repair the tubes. In this decision the commission is supported by the results of the boilers of the "Jeanne d'Arc" and two other similar vessels. Two types of boilers —the Niclausse and the Belleville—are advocated as being the most satisfactory water tubes, though in the case of the Belleville, economizers are deprecated. Either of these two types will be fitted in all future vessels, including those now under construction. It has furthermore been decided that in the full-power and subsequent trials with only 75 per cent of the boilers in use, of vessels, the maximum fuel consumption is to be 22½ pounds of coal and 30¾ pounds per square foot of grate per hour respectively.

The Current Supplement.

The current Supplement, No. 1420, contains a noteworthy series of articles on widely different topics. The salmon investigations of the steamer "Albatross" in Alaska are fully narrated by Commander Jefferson F. Moser, and are illustrated by many striking pictures. Fred T. Jane presents another installment of the Naval War Game between the United States and Germany. In the present installment he tells of the severe defeat and destruction of the German fleet in the Far East. Emile Guarini gives an account of a very novel way of solving the smoke problem. The article describes the method by which the smoke is not consumed, but is commercially utilized in the form of an enriched gas. J. D. Geddes writes on photography as applied to illustration and printing. Charles C. Drueding presents a plain, intelligent treatise on chamois skins. Ceylon tea is now almost as widely consumed as the tea of China and Japan. An article on the tea industry of Ceylon will, therefore, not be without interest. Prof. Asaph Hall, president of the American Association for the Advancement of Science, distinguished the world over for his astronomical work, presents a scholarly paper on the science of astronomy. Prof. Wesley Mills, of McGill University, for a number of years has studied the behavior of animals totally blind in either one or both eyes. He summarizes his studies in an instructive review. The paper on high temperature electro-chemistry by R. S. Hutton and J. E. Petavel is continued.

Electrical Notes.

A patent has just been issued in the United States to Mr. I. M. Hunter for a coin-controlled X-ray machine for public use. The external appearance of the apparatus is similar to that of the automatic cinematograph machines so commonly seen on railway platforms and other places. The observer places a coin in the slot, moves a lever, puts his hand, or whatever he wishes to examine, into a box without any sides, and looks down at it through a fluorescent screen which forms the top of the box. The coin, on being inserted, closes the primary circuit of an induction coil worked by a few dry cells, and the vacuum tube is in a position immediately below the object to be observed.

A novel way to get electricity for lighting a railway train is described by Cassier's Magazine. A dynamo is located on the engine, perhaps under the pilot. Power in driving it is derived from a rotary fan or windmill immediately above, under the headlight. As the locomotive travels at the rate of 20, 30, and even 40 miles an hour, a breeze of corresponding velocity is developed. The current is conveyed to small accumulators under each car of the train. It may be assumed that when these are fully charged, the current is automatically cut off. Tests are said to have been made with an outfit of this kind, and the results are said also to have been encouraging, contrary to what one might be led to expect.

A short time ago the proposal was made and seriously entertained in some quarters to distribute Greenwich time to vessels at sea as well as inland by wireless telegraphy, and, according to our contemporary, Cosmos, Messrs. Burgos, a firm of clockmakers at Ocejos, have devised an apparatus for carrying out the distribution inland. A standard or primary clock determines the discharge of an oscillator at regular intervals. The local or secondary clocks have each an air wire to direct the electric waves on to a detector, which actuates a mechanism and corrects the hands on the dials. We are not aware that the above plan has been put into practice yet, nor is information available as to the results of experiments. The difficulty appears to be that other signals by wireless telegraphy will affect the clocks.

An automatic mechanism which is intended to register the number and class of passengers of a car, the distance ridden by each, the approximate time and place of ingress and egress of each, identifying the conductor, car, trip, day or night, noting the hour or minute of the day or night and the approximate location of the car, in order to obtain a true automatic register or record of the trip and the number of passengers carried independently of the co-operation and beyond the control of the conductor, is an invention for which Frederick W. Brooks of Brooklyn, N. Y., has obtained a patent. The apparatus takes its records in such a manner that they may be used as lantern slides and projected on a screen. An automatic mechanism controls electric circuits and connections to operate a camera electrically, at such intervals or distances apart as may be desired by and in consequence of the revolution of the car wheels. The mechanism is arranged in such a manner that the intervals can be changed or adjusted at will. The camera is so adjusted as to photograph the interior or part of the interior of the car, the platform or platforms and side running boards, and any and all passengers that may come within its field. The camera is so connected with the electrical appliances of the car as to cut off objectionable or conflicting lights. The connections are all protected. The parts of the invention may be briefly summed up as follows: First, a device connected with and operated by the revolution of a wheel or axle of the car and an electrical connection by which the operations of the camera and registers and the distance between such operations are actuated and controlled; second, an electric current from any available source, preferably a battery, either primary or storage, situated in such part of the car as may be deemed most convenient and connected by conductors with the above device, by which the circuit or circuits are opened or closed, the opening and closing of the electric currents being arranged to operate the camera or cameras, the registers, and the lighting and de-lighting of the car; third, a method for automatically lighting the car in such portions as are desired and means for shutting off conflicting or objectionable lights.

A Correction.

In the Scientific American for February 14, there appears an article under the heading "Transporting Lumber Across Deep Gorges," in which credit for the design of the installation described is given to Mr. Edward I. Parsons. We are informed that the system in question was really designed by Percy R. Stuart, of San Francisco, Cal., and we take this opportunity of giving to him the credit to which he is properly entitled.

CURIOUS JADE CARVINGS FROM MEXICO.

BY WALTER L. BEASLEY.

The Mexican Hall of the Museum of Natural History, through original researches and explorations of Prof. Marshall H. Saville, together with recent gifts of the Duke of Loubat, has now on exhibition the most extensive and valuable collection of jadeite objects in the world. The variety and brilliant array of the specimens in design and polish, all exquisitely carved, strikingly illustrate the style and character of the ancient ornaments worn by the kings and aboriginal inhabitants of Mexico and Central America, centuries before the coming of Cortez. One of the astonishing features disclosed by the jadeite collection is the extraordinary skill and perfection displayed in the cutting, drilling, and polishing of the hard stone, so effectively accomplished by these ancient craftsmen. The specimens vary in size from one inch upward, and were obtained mostly in the State of Oaxaca. Prof. Saville found great numbers during his recent excavations among the Zapotecan tombs and temple structures in Oaxaca, which State is now considered to have been the metropolis of the highly-gifted race who occupied this area. The capital, Monte Alban, recently excavated, contained many elaborate palaces and other monumental buildings. The donated collection of the Duke of Loubat numbers some 300 pieces in all, 100 being of pure jadeite, the remainder being of obsidian, serpentine, amazon and turquoise. The collection included several rare and beautiful specimens, among them two gems of their kind being breast ornaments, carved in the shape of a parrot and turtle out of a piece of apple-green jadeite, the most highly prized of all colors. Another interesting carving is in the shape of a highly-polished hatchet, of pure jadeite, only a few of which have yet been found. It is supposed that the hatchet was not intended for practical service, but that it was worn symbolically as a decoration. The body of the extensive collection is composed of breast, ear, and lip ornaments, necklaces of beads, and idols.

The majority of the specimens are profusely sculptured in high relief, the face sometimes in full and in profile, with huge earrings, while in most cases the head is surmounted with the characteristic plumed headdress, like those represented on the ruined structures of Central America. The hat-shaped ear ornaments are nearly two and a half inches in diameter, and are pierced through, leaving thin rims and walls designed supposedly to hold the clusters of feathers which were used in the head-ornaments of that age. The most noteworthy and remarkable piece of jadeite in the collection is a magnificent votive adz, the largest carved specimen of its kind contained in a museum. No other of like dimensions, ornamentation, and archæological interest exists in any of the European museums. All the salient features of this extraordinary relic, notwithstanding its centuries of burial, are still fresh and vivid to the eye of the onlooker. This was found in the State of Oaxaca. In deciphering the figure, Prof. Saville has found a series of markings which make a unit of the whole design; and, from the presence of sharp canine teeth, it is intended to represent a tiger's mask, which was a characteristic feature of Southern Mexican art. On the edge are what appear to be teeth, evidently intended to symbolize the biting or cutting nature of this part of the adz. From the enormous size, weight, and symbolism, it is thought that the adz was used as an idol, or for some ceremonial purpose. The color is light grayish-green, with a tinge of blue, and streaks of almost emerald green in the back. It is 11 inches long by 6 inches wide, and weighs over 19 pounds Troy weight. A portion weighing 2 pounds has been removed for some cause from the back. Dull markings under each eye, ear, and hand evidently were for the purpose of holding plates or rims of gold, which the polished surface would not. The polish on the adz is as fine as that of modern times.

Jadeite was the most highly prized and sacred stone of the ancient peoples of Mexico and Central America, and was supposed to possess great curative properties. The word jade is thought to be a corruption of the Spanish "Ijada," the Nahuatl or Mexican name being Chalchihuitl, meaning a stone of metallic green, like the plumes of the Quetzal. Spanish historians tell us that, when a great dignitary died, one of the important mortuary customs was the putting in the mouth of the dead a stone of jadeite, which they placed as a heart. The natives and poorer classes wore them fastened around their arms and throats as charms to ward off evil and certain diseases. There are two puzzling and extremely interesting problems which have not, as said, been solved by archæologists and other investigators of jadeite, viz., the locality where it was obtained or mined, and how the ancient lapidaries carved, drilled, and sawed this hard stone from blocks. It is certain that an enormous amount of skill and time was employed in their production. The blade of a modern steel knife will hardly produce an impression on the polished surface. No drills, graving or incisive tools giving a clue to the methods of manufacturing them have as yet been found. Cortez, it is claimed by early writers, took back to Spain, among his loot and spoils, some of the rarest and best specimens in the country of jadeite. Some were especially cut and elaborately carved to order. These were presented as a gift to his wife, whose casket of jewels was said to have been the finest of any woman's in

CARVED JADE ORNAMENTS.

Spain. Prof. Saville, through the generosity of the Duke of Loubat, who has done more than any other modern explorer in uncovering the monuments and culture of Mexico's ancient civilization, is confident that in his future excavations and researches in the State of Oaxaca, he will undoubtedly come across the whereabouts of the long hidden jadeite mines and throw new light upon the mysterious and lost art of working this brilliant and precious stone.

SIDE VIEW OF THE CARVED JADE VOTIVE ADZ.

FRONT VIEW OF THE CARVED JADE VOTIVE ADZ.

Fahrenheit's Thermometer.

Writing in Knowledge on the history of Fahrenheit's thermometer, Prof. Cleveland Abbe, of the United States Department of Agriculture, says: "There is every evidence that the Fahrenheit scale began with his use of plus 90 as the upper limit of the temperature of the human body, and minus 90 for the lowest temperature of the air in Europe, and also the temperature obtained by the mixture of salt and ice. Fahrenheit subsequently used a second scale in which plus 12 and minus 12 replaced the plus 90 and minus 90. In 1714, he adopted a third scale, viz., plus 24 for the temperature of the body and zero for the lowest temperature at Dantzic in 1709. His fourth scale was plus 96 for the temperature of the human body and zero for the great cold of 1709. This scale gave him 32 as the temperature of melting ice, but that natural point was not directly adopted by him. With this first satisfactory mercurial thermometer (made in 1721, and whose scale was graduated according to this last system but extended much further upward, by extrapolation) he found that the boiling point of water was constant, or nearly so, at 212 degrees. The fact that Newton's 'arithmetic scale' read 33 or 34 for boiling water, had no influence with Fahrenheit in the formation of his scale."

The Dutch Brine Vegetable Industry.

The cultivation of vegetables for pickling constitutes one of the most important industries of Holland. According to the official record, there are in all about 7,500 acres of farm land devoted to the cultivation of onions, in addition to a number of market gardens which do not enter into the official estimates. About half the entire crop is grown in the province of Zeeland, the remainder mainly in the provinces of North and South Holland. The yield per acre varies considerably with the season, but in the case of the common large onions, the average may be taken at about 300 bushels, though in some years the produce has amounted to over 370 bushels per acre. The areas upon which these onions are grown are usually small, seldom exceeding five acres in extent, and more frequently being about half that size. Small holdings are, however, a general feature of the agriculture of the Netherlands; over three-fourths of the total number of holdings consists of farms of 50 acres and under, and nearly half of this number is represented by holdings of less than 12½ acres each. The small white onions known as "silverskins" are grown mainly in the provinces of Gelderland and North Brabant, though in recent years they have also been cultivated on a small scale in South Holland and Zeeland. The total area sown with this variety does not, however, exceed 125 acres. The growers are mostly small market gardeners or peasant farmers, occupying about 2½ acres of land; a few of them rent larger plots, but their holdings seldom exceed five acres. The rent usually ranges from $17 to $25 per acre, according to the quality of the land, to which is added a rate of 50 cents to 87 cents per week for the cottage. The soil in which the onions are sown is clay, and as its surface elevation is maintained at only a little over three feet above the water level of the dikes and canals, it never gets very dry.

In cultivating silverskins the land is usually marked off into plots about 30 yards wide, separated by furrows. After having been thoroughly cleaned it is manured, then well dug over two or three times with a spade, and finally raked. No horse labor is employed. The manure is applied at the rate of 40 tons per acre. The growers usually produce their own seed by selecting from the crop in autumn the best specimens of small round silvery white onions with thin stalks and few roots. These seed onions are carefully dried and preserved from frost through the winter (either by covering them with earth, hay, or straw, and storing in the open, or by placing them in lofts), and again planted out in the early spring in favorable situations. It is the practice to sow the seed in April, about 56 pounds per acre being used, so that the onions grow closely crowded together. This preserves the whiteness of the bulbs by saving them from too great exposure to the light. On holdings of 2½ acres little outside labor is required, as the occupier is usually able to work the land with the aid of his wife and children, large families being the rule rather than the exception among the small growers. It is the practice to put children to work on the land at 10 or 11 years of age, when they are taken away from school. Sometimes, however, and especially in cases where the area cultivated amounts to 5 acres, occasional laborers are employed to help in digging and clearing the land, and again at harvest, sufficient work being found to occupy two men for about three months in the year. But, wherever it is possible, women and children are employed, as their labor is cheaper. Children are largely employed for picking the onions. Adult male laborers earn 60 to 80 cents per day. Women are paid 50 cents, and children 25 cents a day. The average yield per acre of silverskins in Holland varies from 112 bushels, or 2½ tons, to 7 tons per acre where the seed is sown very thickly.

At a conference of German electrical engineers, Dr. Haas, of Hanover, referred to the electric power supplied for agricultural purposes in that neighborhood. The greatest demand for current is for the operation of threshing machinery, for hay presses, straw-cutters, etc. Of the total horse power installed 77 per cent represents purely agricultural operations and 8 per cent factories. On an average, the annual revenue per horse power installed amounts to 27s., at a price of 2s. 3d. per kilowatt hour, as compared with from 68s. to 146s. in towns, and the average period of use does not reach 150 hours, as against 500 hours in towns. The author concludes from the experience in the Hanover district that satisfactory results are possible in agricultural operations only where cables already exist for the transmission of power or for electric tramways.

RECENTLY PATENTED INVENTIONS.

Agricultural Implements.

AGRICULTURAL IMPLEMENT.—D. Lubin, New York, N. Y. Improvements are provided in this invention for implements operated by motors carried on vehicles. The mechanism is so arranged that the motor will alternately move the vehicle and operate the ground digging and pulverizing tools.

POWER-PROPELLED AGRICULTURAL IMPLEMENT.—D. Lubin, New York, N. Y. This implement is operated by a motor carried thereon; and the object is to provide a device so arranged that while the motor is in continuous operation it will serve alternately to propel the machine and to operate the digging tool, thus making it possible to employ a motor of much less power than needed to propel the machine and operate the digger at the same time.

BARRACK-JACK.—C. Hammond, Woodcliff, N. J. The purpose of this improvement relates to a device for raising the roof of hay-barracks, although it may be used in other connections. In the invention is embodied an arrangement by which the jack is mounted at any height on the pole as contradistinguished from on the ground. The jack is provided with a shank with two studs which may be entered into any two contiguous holes in the post. This enables a very compact jack to be used and avoids using a long connection between the ground and the elevated roof.

BROADCAST HAND SEED-SOWER.—E. C. Smith, St. Louis, Mo. This machine is carried conveniently on the person and operated by hand. Means are provided for securely holding the handle, for covering the seed-opening, for adjusting the gate, so as to regulate the kinds of seeds to be cast over the ground, for adjusting a gage-stop to suit the fixing of the seed-gate, and for arranging the gage-bar with the seed-plate to restrain accidental movement.

BEET-HARVESTER.—C. E. Bartlett, Wayne, Neb. Of the several purposes of this contrivance, one is to adapt it for automatically removing beets from the ground, and means are provided for gradually withdrawing them from the soil and taking them to the rear of the machine by conveyers engaging with the beet tops. Another is to furnish cutters by which when the beets reach the rear of the machine the tops will be severed, the bodies will fall into receptacles, the final receptacle being capable of an automatic dumping action.

AGRICULTURAL IMPLEMENT.—D. Lubin, New York, N. Y. Mr. Lubin provides an implement operated with little exertion and from the action of which all the molecules of the earth operated upon will be set in motion, the action causing a fine separation, as the particles move in all directions, leaving the ground light and porous, thus permitting aeration so essential to fine cultivation. It may be adjusted for different depths of work and operated close to plants safely.

Electrical Devices.

ELECTROMAGNETIC MOTOR.—Angel Pol y Aguirre, Havana, Cuba. This motor consists of permanent magnets secured in two non-magnetic frames, the magnetic poles of which are arranged alternately. Mounted to turn within the series of magnets at both ends thereof, are a double series of electro-magnets constituting a revoluble armature. The twin armatures assist each other in passing dead-points. Each series of electro-magnets has a collector ring connected with every second electro-magnet and a distributing ring to the remainder. Commutators and brushes connect the rings with separate mains of opposite signs.

Engineering Improvements.

PUMP.—W. H. Westerman, Marietta, Ohio. The mechanism employed here relates to that class of pumps adapted to be worked by flexible power-connecting means such as is well known and commonly made use of, where a series of remotely-located pumps are mechanically worked from a common source of power.

STEAM-BOILER.—E. Ward, Mayville, Wis. The part to which this improvement most particularly relates is the "arch" of a boiler. The invention provides a construction easily removed and replaced without disturbing the brick of the boiler-setting at the side or rear walls, whereby the rear end of the boiler can be exposed for cleaning and repairing. The improvement prevents expansion, which would displace brickwork, and the parts are joined so as to do away with bolts and other fasteners.

CONTROLLING DEVICE FOR HYDRAULIC CYLINDERS.—S., W., O. E., C. and H. Hibbard, Sandyhill, N. Y. The invention relates to hydraulic cylinders for use on wood pulp grinders, and is an improvement on an invention previously filed by Messrs. Hibbard. The inventors have perfected a controlling device or valve arranged to cause inflow and outflow of water to and from the cylinder without danger of leaking and to equalize the pressure on both sides of the cylinder-piston to stop the piston whenever desired.

DEVICE FOR RAISING LIQUIDS FROM WELLS.—T. F. Moran, De Young, Penn. Mr. Moran provides in this invention an improved device for raising oil and water from deep wells, more particularly oil-wells. The device is so arranged as to prevent the escape of the natural gas, utilizing its pressure in raising the oil to the surface. This pressure is assisted by compressed air pumped into the well.

Mechanical Devices.

MARKING-MACHINE.—C. S. McGhan, Junction City, Kan. In perfecting this improvement the inventor supplies a mechanism for stamping and marking in general, but particularly adapted for stamping linen or sheets of fabric or other material, these being interposed between a type-bearing wheel and an elastic pad secured upon the table.

SPEED-INDICATOR.—C. E. Kelly, Anderson, Ind. Two patents have been granted Mr. Kelly for improvements in speed indicators. One invention provides an indicator which may be conveniently applied to indicate the speed or movement of any machinery, such as the speed of a wheel in traveling over the ground.

The other invention relates more particularly to a centrifugally controlled means for transmitting movement to a speed indicator. The device comprises a casing in the form of a hub which may be fitted to any rotary part. Within this casing a number of spherical weights coacting with inclined planes serve, when actuated by centrifugal force, to transmit the movements to a ring outside of the casing.

MAIL-CATCHER ARM.—F. M. Edwards, New York, N. Y. When the arm of this device is not required it can be locked at the center of its supporting-bar within the plane of the outer surface of the door-joint, and the arm may be reversed to bring its receiving end facing the direction of travel of the train and then brought to a receiving position beyond the door-jamb and locked at either end of its supporting bar. An automatic locking device is provided which offers no hindrance to the reception of a bag on the arm, but which acts to prevent the bag leaving until purposely removed.

MAIL-DELIVERER.—F. M. Edwards, New York, N. Y. This mail-deliverer is capable of ready attachment to the door-jamb of any mail-car and will not interfere with the use of the door. It is so made that a mail-bag may be quickly attached thereto at the top and bottom of the bag, the fastening device in no way stopping the safe and quick removal of the bag from the deliverer. The deliverer is held parallel with the side of the car within the doorway or extends out from the doorway at right angles to the side of the car. A crane is used with the deliverer, and it has supporting-arms for the bag like those of the deliverer.

MACHINE FOR CUTTING ARTICLES FROM THE INSIDE OF SHOES.—W. S. Fulte, New Orleans, La. In operating this device, the shoe is turned bottom upward and slipped over the cutting mechanism. The workman works the shoe around over the neck, so that the cutters come in contact with the nails or tacks, cutting them out completely. By manipulating the shoe the cutters can be forced into the remote parts of the toe. The hand need not enter the shoe while the cutters work. The neck protects the gearing and the shoe.

COKE-DRAWER.—W. S. Jones and J. P. Donohoe, Greensburg, Penn. The invention comprehends a carriage held to travel in front of the coke-oven and includes a platform, for sustaining the operator, reciprocal in the longitudinal plane of the oven. The carriage has a nose adapted to penetrate through the oven-door, with means for attaching the scraper and holding it in a position under the operator's control. Thus the scraper can be set in the coke at desired points and be pulled by the outer movement of the platform to draw the heavy coke bunches out through the oven-door. An endless conveyer receives the coke and conveys it to any suitable receiver.

Railway Improvements.

RAIL-JOINT.—F. S. Pascoe, Allegheny, Penn. Mr. Pascoe's invention refers to rail-joints and it provides a simple construction whereby the joint may be securely locked when applied and the locking key retained in position by the locking device.

AUTOMATIC TRIP-BRAKE.—E. L. Cridge, Passaic, N. J. In the design of this improvement on automatic trip-brakes for railway vehicles, the object is to stop such vehicles automatically in case the engineer for any reason disregards the danger-signal. The invention thus affords an efficient device for preventing railway collisions.

CAR-FENDER.—J. Eoclandt, New York, N. Y. The object in this invention is to provide a fender that will be quickly lowered when a part comes in contact with a person or other obstruction, and thus prevent the car from running over the same. Means are furnished whereby the motorman may raise the fender to its normal position.

TRACK ATTACHMENT.—W. H. Crossley, Bloomsburg, Penn. Mr. Crossley has invented an improved attachment designed to prevent fire hose run across the tracks of a street railway from being injured by the car wheels and at the same time obviate the interruption of travel. The attachment consists of a bridge which can be easily applied to a track to lead over the fire hose.

Miscellaneous.

CARBURETER.—A. H. Rife and J. B. Carper, Dallas City, Ill. This carbureter belongs more particularly to the type used in so-called "vapor-stoves," which burn gasoline and similar hydrocarbons. Four distinct vaporizing operations of the gasoline are effected. First, by contact with the heated plate; second, through close contact with the heated gauze; third, by a wick arrangement vaporizing by capillary attraction; fourth, where vaporization is due to a cup located immediately adjacent to an auxiliary flame and which receives any liquid remaining after previous vaporization.

APPARATUS FOR FORMING BLAST-FURNACE CHARGES.—A. S. Dwight, New York, N. Y. Provision is made in this apparatus for forming blast-furnace charges in a very simple manner, the arrangement being such that the charges prepared are of a certain composition and of approximately equal weight and the ingredients thoroughly mixed. Thus much saving of time and labor is effected.

LOOSE-LEAF LEDGER.—F. B. Towne, Holyoke, Mass. This is an improvement on a patent previously issued to Mr. Towne. The ledger or book is doubly locked owing to means for confining the leaves, few or many, securely in place and to the use of locking devices which hold the covers and back rigidly together, while the covers may open freely and the back lie flat on a desk. A stay bar connects the post against spreading under the leaves. Means are provided for obtaining access to the locking-slat and leaves on the post and also for enabling the leaves to be put in or withdrawn easily without tearing.

INDICATOR FOR TOILET-ROOMS.—E. D. Allen and W. A. McElney, Meriden, Conn. This device is easily applied to existing structures. It is so arranged that it will automatically indicate whether a toilet room is occupied or vacant. It is adapted especially for railway-cars, and advantageously for rooms of hotels, houses and other places. It may be applied to a sidewall of a toilet-room or to the door and used on doors swinging in or out and also in connection with full or with half doors. The same effect may be had from the door bolt as from the floor.

HASP-FASTENER.—A. Keller, Paris, Ill. This efficient device cannot be readily tampered with or unfastened. As the hinge is set down within the woodwork and has no pintle it offers no projections on which a chisel could be used. If a pintle were employed and the hinge projected, the pintle could be cut and removed, rendering the device useless. It is a superior fastener for boxes, trunks, car-doors, cell-doors, etc.

TRANSFERABLE JOB-BANK.—G. M. Green, O'Neill, Neb. This transferable job-bank consists of a flat slab provided with a rib at the lower end and a number of compartments sunk flush with the surface at the upper end. The bank is supported at an inclined position by angle braces. The many uses to which the device and particularly the compartments can be applied will be obvious to printers.

PURSING-SEINE.—W. F. Harris, Gloucester, Mass. With seines as heretofore used considerable difficulty has been experienced when circling around a shoal of fish by reason of the heavy metal rings attached to the foot of the seine which tend to drag the small fixed boat toward the fish, frightening them off before they are completely surrounded. This difficulty is obviated by the present invention.

CLIP-APPLIER.—G. J. Van Schott, Passaic, N. J. The efficiency of surgical appliances is advanced by this implement, which engages and presses a clip in position on a superficial flesh wound to close the same, the clip being preferably of the construction shown and described in a previous patent granted to Mr. Van Schott.

HAT-PIN AND FASTENER.—C. B. Garrison, Cincinnati, Ohio. Means are here provided for mounting hat-pins in a hat so that the pins may be moved freely into and out of operative position without actually detaching them from the hat, while the devices employed permit the removal of the pin when desired. The formation of holes is avoided and the pin is firmly held.

NON-REFILLABLE BOTTLE.—P. J. Atzbergen and F. W. Peters, Cleveland, Ohio. The main purpose of the inventors is to furnish a bottle so constructed that after it has been emptied of its contents it cannot be refilled and again presented as an original package. They have provided one of this character conveniently made and substantially of the same shape as an ordinary bottle.

ANIMAL-TRAP.—V. Weiler, Lincoln, Neb. This structure is capable of trapping small animals, the size of rats and mice. It is a sensitive tripping mechanism. The slightest weight compels the quickness and certainty of operation, and the tripping part is so related to the bait-holder that the animal in its efforts to reach the bait must engage with the movable member, which springs the trap and drops the captive into the cage. The tripping devices form a runway and serve to close the subjacent cage, and they include automatic locking and setting parts.

CALENDAR.—A. F. Hoffman, New York, N. Y. The invention provides a simple and neat calendar which will indicate comparative dates for different years and their subdivisions. It comprises a board or base on which are secured twelve pads, one for each month. Each pad contains detachable leaves for the days of the month. Beneath these is a leaf containing the table for the entire month, while under this leaf is printed a table for the corresponding month of the previous year.

Note.—Copies of any of these patents will be furnished by Munn & Co. for ten cents each. Please state the name of the patentee, title of the invention, and date of this paper.

Business and Personal Wants.

READ THIS COLUMN CAREFULLY.—You will find inquiries for certain classes of articles numbered in consecutive order. If you manufacture these goods write us at once and we will send you the name and address of the party desiring the information. **In every case it is necessary to give the number of the inquiry.**
MUNN & CO.

Marine Iron Works. Chicago. Catalogue free.

Inquiry No. 3917.—For makers of machines for cutting railway ties.

Autos.—Duryea Power Co., Reading, Pa.

Inquiry No. 3918.—For dealers in coal oil.

"C. S." Metal Polish. Indianapolis. Samples free.

Inquiry No. 3919.—For dealers in telegraph instruments of all kinds.

For bridge erecting engines. J. S. Mundy, Newark, N. J.

Inquiry No. 3920.—For manufacturers of toys.

Coin-operated machines. Willard, 284 Clarkson St., Brooklyn.

Inquiry No. 3921.—For makers of small metal boxes, iron, brass or aluminium, in the line of match safes.

Blowers and exhausters. Exeter Machine Works, Exeter, N. H.

Inquiry No. 3922.—For makers of windmill pump cylinders in which plungers on pistons are used that work without leathers.

Handle & Spoke Mchy. Ober Mfg. Co., 10 Bell St., Chagrin Falls, O.

Inquiry No. 3923.—For a self-acting dividing engine for dividing 3 to 6 inch theodolites.

Dies, stampings and armature discs. Advance Manufacturing Co., Racine, Wis.

Inquiry No. 3924.—For wholesale dealers in mail order goods and rubber suitable for making rubber stamps.

Sawmill machinery and outfits manufactured by the Lane Mfg. Co., Box 13, Montpelier, Vt.

Inquiry No. 3925.—For the manufacturers of the Edison storage batteries.

For Sale.—60 h. p. Otto gas engine, the latest type, practically new. Colborne Mfg. Co., Chicago.

Inquiry No. 3926.—For manufacturers of brass numbering tacks for fly screens.

Let me sell your patent. I have buyers waiting. Charles A. Scott, Granite Building, Rochester, N. Y.

Inquiry No. 3927.—For manufacturers of sugar machinery and driers.

Machine Work of every description. Jobbing and repairing. The Garvin Machine Co., 149 Varick, cor. Spring Sts., N. Y.

Inquiry No. 3928.—For a 21-foot gasoline river launch fitted with good 2 to 4 h. p. engine.

Manufacturers of patent articles, dies, stamping tools, light machinery. Quadriga Manufacturing Company, 18 South Canal Street, Chicago.

Inquiry No. 3929.—For makers of suspender buckles, etc.

The best book for electricians and beginners in electricity is "Experimental Science," by Geo. M. Hopkins. By mail, $5. Munn & Co., publishers, 361 Broadway, N. Y.

Inquiry No. 3930.—For makers of pyrometers for bake ovens.

The largest manufacturer in the world of merry-go-rounds, shooting galleries and hand organs. For prices and terms write to C. W. Parker, Abilene, Kan.

Inquiry No. 3931.—For makers of sheet metal spinning and polishing lathes, also makers of novelties such as can-openers, cork screws, etc.

The celebrated "Hornsby-Akroyd" Patent Safety Oil Engine is built by the De La Vergne Refrigerating Machine Company. Foot of East 138th Street, New York.

Inquiry No. 3932.—For information about a crematory for disposing of refuse and garbage of a large town.

For Sale.—United States patent right of feed trough for poultry or swine. Price moderate. Copy of patent free.
Jno. Ahrends,
Sunman, Ind.

Inquiry No. 3933.—For a strong horseshoe permanent magnet capable of lifting 15 or 20 times its own weight.

Wanted—Revolutionary Documents, Autograph Letters, Journals, Prints, Washington Portraits, Early American Illustrated Magazines, Early Patents signed by Presidents of the United States. Valentine's Manuals of the early 40's. Correspondence solicited. Address C. A. M., Box 773, New York.

Inquiry No. 3934.—For manufacturers or business concerns that will have an exhibit at the St. Louis Exhibition.

Patent No. 701,951 for sale or royalty. The strongest and most rigid adjustable alligator wrench invented.
Wm. Shirk, Panama, Iowa.

Inquiry No. 3935.—For parties to make odd-shaped bottles reasonably.

For Sale. Thornycroft steam wagon, good condition, 23 h. p., speed 8 miles, capacity 5 tons. Address W. L. M., 82 Cotton Exchange Building, N. Y. City.

Inquiry No. 3936.—For machines for embossing leather and fiber chair seats.

Inquiry No. 3937.—For parties handling the Edison "Loud Speaking Telephone" and the Hewitt mercurial vapor lamps.

Inquiry No. 3938.—For automatic weighing machines for sacking and weighing grain.

Inquiry No. 3939.—For makers of electric blue print machines.

Inquiry No. 3940.—For makers of electro-magnets with disk armatures for use in pipe organ actions.

Inquiry No. 3941.—For makers of electric clocks for hotels, schools and factories

Inquiry No. 3942.—For a machine for winding fine wire.

Inquiry No. 3943.—For a steel hull 30 feet long, flat bottom, to draw not over 10 inches loaded, propelled by stern wheel driven by gasoline engines.

Inquiry No. 3944.—For makers of kerosene oil pressure lamps on the Kitson principle.

Inquiry No. 3945.—For makers of wooden novelties, such as spoons, forks, bowls, plates, etc.

Inquiry No. 3946.—For makers of polished hardwood bases suitable for telegraph instruments.

Inquiry No. 3947.—For information as to machines for making pyroligneous acid.

Inquiry No. 3948.—For makers of hard rubber goods, such as telephone receivers, hard rubber tubing, etc.

Inquiry No. 3949.—For a second-hand gasoline engine between 3 and 5 h. p.

Inquiry No. 3950.—For address of parties making small gas engine castings with drawings.

Inquiry No. 3951.—For castings and connections for a small electric motor.

Inquiry No. 3952.—For a machine for manufacturing wooden oars

Inquiry No. 3953.—For the manufacturer of the collapsible lifeboat which was recently tested at the Brooklyn Navy Yard.

Inquiry No. 3954.—For crude rubber and asphaltum used in the manufacture of roofing paints.

Notes and Queries.

HINTS TO CORRESPONDENTS.

Names and Address must accompany all letters or no attention will be paid thereto. This is for our information and not for publication.

References to former articles or answers should give date of paper and page or number of question.

Inquiries not answered in reasonable time should be repeated; correspondents will bear in mind that some answers require not a little research, and, though we endeavor to reply to all either by letter or in this department, each must take his turn.

Buyers wishing to purchase any article not advertised in our columns will be furnished with addresses of houses manufacturing or carrying the same.

Special Written Information on matters of personal rather than general interest cannot be expected without remuneration.

Scientific American Supplements referred to may be had at the office. Price 10 cents each.

Books referred to promptly supplied on receipt of price.

Minerals sent for examination should be distinctly marked or labeled.

(8877) A. J. R. writes: I have a small machine requiring about ¼ horse power to operate, and which we run continuously, and am desirous of getting some economical power to operate and run it, and write to ask if there is anything on the market more economical and satisfactory than the gasoline engine, and would it be possible to so arrange gears as to run the machine by clockwork, or weight or spring? A. There is no power in a small way so good or so cheap to run as a gasoline motor. You should have for your work one of a half horse power. Weights or springs have to be wound up, and only give out power for a very short time, and not all that is put into them in winding. They have been tried for useful work, and have been given up as only suitable for clocks, small fans, and for turning images and goods in show windows.

(8878) H. H. asks: Will you please tell me how much air compressed to 100 pounds pressure will expand when released? The quantity of air released to reduce pressure one pound. A. The air released from 100 pounds pressure will expand 4¼ times its volume. The quantity released to reduce the pressure one pound must be 0.068 of the volume of the air holder.

(8879) W. V. H. writes: Inclosed you will find drawing describing at the bottom what it will do. Please explain why the motor reverses when wire is connected at *A*. A. When one cell is used in your Porter motor as shown in your diagram, the motor runs as a series motor. When you connect the second cell, the armature or the field, as you may look at it, is reversed, and the direction of the rotation of the armature is reversed. To reverse the current in both field and armature does not reverse a motor; to reverse one of these alone does reverse the motor.

(8880) F. A. H. writes: I am producing, in an induction coil, alternate currents in the secondary by employing, instead of the usual contact breaker, the change from highest to lowest resistance in the primary, just as is done in the telephone with the transmitter in series with the primary of the coil. I learned from you some time since that these secondary currents could be made pulsating direct by the use of a condenser. This has been argued against by others whom I have since been in connection with. Will you kindly advise me just how to accomplish the desired results, either with the contact breaker or, for instance, the transmitter, should it be possible? A. With a condenser attached to an induction coil, the spark at the break of the circuit in the vibrator is made much longer than the spark at the making of the circuit through the primary. Hence if the spark terminals are drawn apart so far that no spark passes on the closing of the primary circuit, only the spark at the break can pass, and that will always be in one direction. The secondary current becomes a pulsatory unidirectional current. When the spark terminals are near enough to each other, the secondary current passes both at the make and at the break of the primary circuit, and an alternating pulsatory current is produced in the secondary winding.

(8881) C. D. S. writes: We have a pancake griddle using charcoal which is not a success. I would like to convert it into an electrical one. The size is 2 feet 5 inches by 1 foot 3¾ inches. How much and size of steel wire would be required to raise it to the right heat at 110 volts pressure? A. We do not advise you to attempt the winding of an electrical griddle. The danger of fire is too great. Special asbestos insulation is required by the underwriters for such articles, and you would find it far cheaper in the end to purchase an article made to conform to the requirements of the insurance companies. We do not know the temperature of a griddle nor do we know the allowance to be made for radiation in such a large surface exposed to the air. Much practical experience in designing cooking utensils is needed to answer your question. You will probably need to use from 5 amperes to 15 amperes at the various heats. You would then require 22 ohms of wire so arranged as to be cut out by a switch to 7 1-3 ohms. You can obtain griddles of all sizes from the American Electric Heating Corporation, 1137 Monadnock Block, Chicago, Ill.

(8882) O. F. asks: Will two coils of insulated copper wire attract one another when an electrical current is passed through them in the proper directions? What is the maximum of attraction obtainable expressed relatively to the weight of the coils? A. A coil of wire carrying a direct electric current is an electromagnet, and two such coils will attract each other as two electromagnets will do. The attraction depends upon distance, mode of winding, amount of iron on the cores, etc. To determine the attraction of the coils you would use you should make and try them. You cannot use the alternating current in an electromagnet.

(8883) A. G. P. asks: For a magnet with cores 1¼ x 5-16 inch what size wire should I use to get the strongest magnetism when wound the multiple-wire method? Will a magnet wound this way be as strong as one wound the regular way? About what is number of pounds pull on the tailpiece of a guitar when the instrument is in tune? A. There is no need to wind a small bar of iron by a multiple wire to obtain its magnetic saturation. Use any convenient number of wire from 20 to 24 and wind the spool to a depth of ¼ to 1-3 inch. Then two to four cells of battery will make it lift its full load. The theoretical lifting power would be 15 pounds which it is not probable you can reach. We are not able to give the pull upon the tailpiece of a guitar. If you have a spring balance, you can easily measure it by taking each string separately and tuning it to its note with one end attached to the hook of the balance. Get the strain in pounds for each string, and add the separate pulls together. You can do the same thing by using weights or stones instead of a balance and weighing them. The exercise of your ingenuity will enable you to do your own investigating, and be of more benefit to you than if we could tell you directly.

(8884) I. C. R. asks: What will make silk waterproof and stiff at the same time? A. After the silk has been soaked in glue and dried, it should be digested for several hours in a solution of alum; this will make the glue insoluble, and therefore waterproof. Or the glue may be rendered insoluble by digesting the treated silk in a weak solution of formaldehyde. Casein can be used in place of the glue; after drying the treated silk, the casein can also be rendered insoluble by formaldehyde.

(8885) H. K. asks: How can I connect 12 3½-volt lamps, consuming between 50 and 60 amperes each, on a 108-volt alternating current? Lamps are a trifle over 1 candle power. A. You cannot connect 12 3½-volt lamps economically to a circuit with 108 volts in it. The twelve lamps have 42 volts in series. You can connect them in series to a resistance, or inductance coil, and thus light them. You should apply to the company furnishing the current for the connection, and they will fit you out with the proper apparatus. Such low-voltage lamps are made for battery use, and ought not to be put on a high-voltage circuit.

(8886) D. H. F. asks: What percentage of shrinkage is there in the casting of brass? That is, how much larger should the pattern be to give the proper dimensions? A. The shrinkage allowance on patterns for casting brass should be 3-16 of an inch per foot in length or diameter.

(8887) F. S. P. asks: Can you furnish me with a recipe giving full directions for making Flemish oak finish? A. The wood is smoothly surfaced, and a solution of copperas containing one ounce in two quarts of water is brushed over. Follow this with an oil stain mixed with sienna or umber and drop black to color desired. Finish by waxing the wood one or more coats to get the desired effect, leaving the grain rubbed off smooth and open.

(8888) C. J. S. asks: Can you tell me how to make an electro-magnet to be used on 100-volt alternating current? A. An electromagnet cannot be used upon an alternating current. They are employed with a direct current. The alternating current flows first in one direction and then in the opposite direction through the circuit, so that the poles of the magnet are reversed at each alternation. Such an arrangement is not servicenble.

(8889) S. G. asks: What is used in the mantle of the Welsbach which gives to it its brilliancy, and in what manner is it applied; and also what change or action is it, chemically or physically, that causes the mantle to glow so brilliantly? A. The Welsbach mantle is made in the following manner: A net is woven out of thread, and this is then thoroughly impregnated with a solution of the mixed nitrates of thorium and cerium, in the proportions of 99 per cent of the former to 1 per cent of the latter. It is put on the market in this shape. Now, when a match is touched to it, the thread burns away, and the nitrates are decomposed to the respective oxides, and there remains therefore a coherent web of these oxides having just the shape and structure of the original net. Primarily, the luminosity is caused by the high temperature, just as is the case with the ordinary lime light, the heat rays of the flame being raised to light rays. Just why a mixture of thoria and ceria, containing one per cent of the latter, gives the maximum intensity of illumination, has not been definitely proven, though various theories have been advanced. Measurements with a thermo-element show that in the same zone of the Bunsen flame, this mixture will attain a higher temperature than either thoria or ceria or any other earth, if alone; while this does not explain why it attains a higher temperature, it does explain why there is greater luminosity.

(8890) D. McK. asks: How much does a bushel of vermilion red weigh? How much does a bushel of yellow ocher weigh? What is the specific gravity of red lead? What is the specific gravity of white lead? Do vermilion red and red ocher mean the same thing? A. Ocher is very variable in character and weight; a Winchester bushel will weigh from 125 pounds to 170 pounds. As Venetian red is also equally variable, its weight will also vary, but runs somewhat higher than ocher. The specific gravity of red lead is about 9; of white lead, about 6.5. Venetian red is made by burning ocher; the term red ocher is rather unusual, but it would probably be the same as Venetian red.

(8891) C. T. J. asks: 1. What is the equivalent of one H. P. in man power: i. e., about how much man power equals one H. P.? A. For constant work a horse power is equal to the work of 8 men. 2. What is the reason that two *platinum* strips are always placed in the acidulated water to be decomposed by an electric current? Why couldn't two strips of any other metal that is a conductor of electricity be used? A. Platinum is employed as electrodes in decomposing water because it is not attacked chemically by either the oxygen or hydrogen of the water when they appear upon it as nascent gases. It is the cheapest metal, if not the only one, of which this is true. Hydrogen can be collected by the use of carbon electrodes; but the oxygen combines with the carbon to form carbon dioxide, which can be collected if desired. Oxygen cannot be collected from carbon. 3. Could a small electric motor, say ¼ or ½ H. P., to be run on a 110-volt, 5½ or 6 ampere, alternating current, incandescent lighting circuit, be started and stopped by means of a switch only, or would a rheostat also be necessary as with the larger sized motors on circuits of higher voltages? A. A small electric motor is usually provided with the proper coils for starting and running at two or three speeds in the machine itself. The switch then has three or four points, and is fastened to the frame of the motor. It is more convenient to place these in a separate place in a large motor. 4. Would you please state the difference between the induction coil used in connection with the X-rays and telephony, and the inductance coil used in wireless telegraphy? A. An induction coil has two windings, the primary and the secondary. A current in the primary induces another current in the secondary, of a different voltage and current strength in amperes. Such are Ruhmkorff coils and transformers generally. An inductance coil has a single winding, usually without iron, to act as a restraint upon the rush of the current through the circuit. This it does by the counter electromotive force produced in the coil by its self-induction. Its effect is produced not merely by its resistance in ohms, but also by the impedance due to the reactance of the turns of the coil upon the current. 5. About what would be the voltage and the amperage of a Wimshurst frictional electric machine having its two circular discs of glass 16 inches in diameter (each), the glass being 1-16 inch thick? (Machine gives a spark 1½ to 2 inches long.) A. The voltage corresponding to a given length of spark cannot be stated in exact figures. It depends upon a number of factors: whether plates or balls are employed as terminals, and their size in each case; also upon both temperature and pressure of the atmosphere. A good discussion of this is to be found in Thompson's "Elementary Lessons." About 28,000 volts are usually given as the pressure needed to force a spark through one inch of dry air. 6. About what would be the voltage and the amperage of a No. 4 Laclede sal ammoniac cell? What would it be, and how is it calculated, for a battery of three such cells in series, in multiple? A. The Laclede cell has about 1.4 volts on open circuit, as do all the various forms of sal ammoniac cells. On closed circuit it quickly falls to 1 volt or less, if the current is as great as two-tenths of an ampere. Upon opening the circuit they recover quite well, since they have so large an area of carbon. Three cells in series will have three times the voltage of one; in multiple they will have the same voltage as one cell. The amperes cannot be given since they depend upon the resistance of the external, as well as upon the internal resistance of the cells. 7. I have read that some damage might be done to a storage battery by overcharging, but that there is always more or less damage done by over-discharging. Could you please explain how this (over-discharging) damages the battery, and is there any way in which to prevent it by simply observing the lead plates or the sulphuric acid and water in which the plates are immersed, in a simple home-made cell not equipped with measuring instruments? A. Over-discharging injures a storage battery by converting too much of the active material. It reduces a battery to too feeble a condition. It may even be carried so far that it is scarcely possible to charge the cell properly again. See Treadwell's "Storage Battery" for more instruction upon these matters. No storage battery should be run for work without having the proper instruments for indicating its condition.

(8892) G. J. V. asks what are the ingredients used in the manufacture of lava insulators; also enamel on the backs of resistance plates. A. The enamels used on insulators are the same as are used on dishes. There are many formulas. A good one is: Take quartz, 100 pounds, calcined and ground; borax glass, ground, 50 pounds. Mix, fuse in a crucible, and let cool slowly. Powder 40 pounds of this glass, and mix with 5 pounds of white potter's clay. Grind the mixture to a fine paste in water. Apply to a clean surface, and let it stand in a warm dry place to dry. After this, it is burned in an oven. A glaze can be put upon this by using a powder of white glass 125 pounds, borax 25 pounds, carbonate of soda, fused and powdered, moistened and dried, 20 pounds. To 45 pounds of this add 1 pound soda. Mix thoroughly and dry. Then reduce to a fine powder. Dust the surface of the enamel while still moist with this powder, and then bake. Several coatings of the glaze may be put on, one after another. The lavas are made of fine clays baked as porcelain is treated. For many receipts for doing this see "Cyclopedia of Receipts."

(8893) O. C. S. writes: A friend of mine claims that the wheels of a railroad car slip sideways only when rounding a curve. I claim that they also have what I shall call, for want of a better expression, a rotary slip; that on a slow-moving train the outer wheels slip, while on a faster train the inside wheels slip. What are the facts in the case. A. The wheel flanges of railway cars bear against the outer rail when rounding a curve by their momentum, and against the inner rail when strongly pulled by the locomotive. The inner and outer wheels both slip, the inner one forward and the outer one backward, according to the conditions of running on a curve. The centrifugal force at high speed throws the greater weight on the outer wheels, when the inner wheels slip forward.

(8894) C. E. H. asks: If we take a Bunsen burner using good fuel gas, capable of 700 heat units per cubic foot, and burn this with a naked flame, the heat resulting from each cubic foot of gas consumed would be diffused into the surrounding atmosphere, and would raise the temperature as high as 800 units. Now, if we take the same burner and surround it with a sheet metal tube after the manner of an ordinary gas radiator, and in addition to the tube place two or three metal deflector plates at a convenient distance above the flame, so as to have as much radiating surface as possible, we find under these conditions the temperature of the surrounding atmosphere is raised very much higher than it would with the naked flame, although we are using the same burner and producing approximately the same number of heat units per cubic foot of gas. How do you explain this increased efficiency for heating? A. Your difficulty with the difference in the heating power of gas when burned with an open flame or with a radiator is easy of explanation. When the open flame is used, the heat is carried up to the ceiling in a strong current of air, and the upper part of the room is much hotter than the lower part. The heat is lost, since we do not live up there. A radiator does just what its name implies—stops the rising of the heat. The heat of the flame is communicated to the metal of the radiator, and this acts as the real heater. It sends out the heat, down and all around with equal facility. You can test this with a thermometer, and see how the air below the radiator is heated. With the open flame the space below the flame is cold, by reason of the draft of cold air drawn in to feed the flame. Radiant heat travels down as easily as it rises. Convection currents of air always rise, and carry the heat up with them.

(8895) G. H. B. says: I have just commenced to nickel-plate, and am plating for a large stove firm; they have all one can do. I have turned out some fine work, but some of the nickel will peel off. As I am a beginner, I have used nickel salts and single salts for the exposed parts. I was told to plate the pieces in nitrate of copper first, to make the nickel adhere better. I tried it, but did not get any copper plate on. Please tell me the best way to get the best results of platings. A. The peeling off from some of the work is probably due either to imperfect cleaning of the object or by using too strong a current. The failure with the copper was due to the use of the nitrate of copper, with which it is practically impossible to do any plating. Copper sulphate, copper acetate, or copper carbonate, together with sufficient potassium cyanide to make the double salt, is the proper material to use. See "SCIENTIFIC AMERICAN Cyclopedia of Receipts," article on "Electro-metallurgy."

(8896) H. M. H. asks if hard woods can be used in the manufacture of wood pulp. How fine wood is ground for the pulp? To what process is the wood submitted after being ground, and in what shape is the pulp put for the market? A. Hard woods are not used; spruce and the other pines give the best pulp; linden and aspen give a whiter pulp, but of inferior quality. After grinding, the mass is beaten to complete the disintegration and hard woody masses are separated. The pulp is then collected in endless screens and pressed between rolls.

(8897) A. F. S. asks: Does not liquid oxygen as produced by liquid air become opaque to magnetism, that is, is it slightly attracted by a magnet? A. Oxygen was discovered to be a magnetic substance by Faraday in 1849, by noting that it was attracted to a magnet pole just as iron is, though to a lesser degree. Becquerel was the first to call attention to the subject in recent times. In 1892 Dewar, having produced liquid oxygen in large quantity, renewed the matter and showed that liquid oxygen has about one-thousandth of the magnetic moment of iron. Liquid oxygen is shown in a tube swinging to the pole of a magnet, in Sloane's "Liquid Air," page 337, but the language used in the text describing the experiment is not correct. It should read: "Oxygen was discovered to be *magnetic* by Faraday." The fact is just the opposite of the statement of the book.

(8898) R. R. J. asks what voltage is required to jump a spark gap of ¼ inch, and if the voltage is in direct proportion to the width of spark gap. Also, how to determine the number of oscillations and wave length wireless telegraph system as mentioned in SUPPLEMENT, No. 1383, Siemens & Halske system or any system. A. The voltage necessary to force a spark through ¼ inch of air varies greatly with the shape of the terminals, as points, balls or plates; and with the pressure, moisture, and temperature of the air. Thus a spark 1-5 inch long was produced between balls 1-10 inch in diameter by 16,200 volts; and between balls 1 inch in diameter by 18,900 volts pressure. The subject is quite fully treated in Thompson's "Elementary Lessons." The methods of measuring lengths of electrical waves will be found in papers given before the American Institute of Electrical Engineers. Prof. Pupin has presented several papers upon these topics, which we cannot abstract in a letter.

(8899) S. M. G. inquires whether a jump spark coil can be made by single windings instead of primary and secondary windings. If so, what size wire and how heavy insulation is best for a current of 5 to 8 volts pressure? A. A coil can be made for gas lighting and similar small uses with one winding; but a jump spark of sufficient length to make a sure ignition in a gas engine should be an induction coil with primary and secondary windings. A spark coil with one winding may be made with a core 10 inches long, covered with paper. The winding should be of cotton-covered magnet wire, say No. 14, of which 300 feet or thereabout may be wound on. The spark is given at the breaking of the circuit, and is due to self-induction. Each layer may be separated from the adjacent layers by brown paper, not very thick. No very definite rules are required, as there is a great difference to be noted among these coils. The battery may vary, and as it runs down, more cells may be attached.

(8900) A. B. C. asks for a formula for oxidizing linseed oil without litharge; want to have oil very heavy and bright, and entirely free from fat. A. Keep the oil at a temperature of somewhat over 130 deg. C., while a current of air is passed through or over it; then increase the temperature until the oil begins to effervesce from evolution of products of combustion. By continued boiling the oil becomes very thick and may be drawn out into elastic threads, which are very sticky, but do not produce a greasy stain in paper.

(8901) R. F. D. asks: In the Planté type of cell, how many square inches of positive plate surface are reckoned for one ampere-hour? By Planté type I understand that metallic leaden plates are immersed in the electrolyte, which I suppose is correct. A. The Planté type of secondary cell is defined by Foster in his "Electrical Pocket Book" to be "constructed of lead plates so designed as to present a large surface area to the action of the electrolyte, the active material being formed on the plates, either electrically by charging and discharging, commonly called forming, or chemically." The same authority gives a formula for calculating the theoretical capacity of a cell per pound of active material. This is the better way of expressing it, since to base the capacity upon the surface will not take the thickness into account. The *practical* results given are: For lead peroxide and the same weight of spongy lead per ampere hour: 0.53 ounce for a ten-hour rate of discharge; 0.62 ounce for a five-hour rate of discharge; 0.70 ounce for a three-hour rate of discharge; 1.00 ounce for a one-hour rate of discharge. These numbers are for plates of ordinary thickness and an electrolyte of the density of 1.200.

(8902) P. S. B. wants to know the composition and the method of manufacture, of carborundum. A. The mixture from which carborundum is produced consists primarily of coke and sand, to which is added a small amount of salt to facilitate fusion, and a small amount of sawdust, which evolves gases upon heating, and these gases tend to keep the mass more porous and thus facilitate the escape of the carbon monoxide gases later produced. This mixture is packed between the two carbon poles carrying the current, there being, however, a central core of coke placed directly between the carbon poles, providing thus a conductor for the current and so overcoming the difficulty of starting up, and also keeping the internal resistance more uniform by breaking up the arc into numerous small arcs. Carborundum is a silicide of carbon; the formula is CSi.

WOOD or METAL Workers



Without Steam Power should use our Foot and Hand Power Machinery. Send for Catalogues A—Wood-working Machinery, B—Lathes, etc.
SENECA FALLS MFG. CO.
695 Water St., Seneca Falls, N.Y.

ENGINE & FOOT LATHES. MACHINE SHOP OUTFITS TOOLS & SUPPLIES
SEBASTIAN LATHE CO. 120 CULVER ST. CINCINNATI, O.

Wire Cloth, Wire Lath, Electrically-Welded Wire Fabrics
and Perforated Metal of all Kinds
Manufactured by
CLINTON WIRE CLOTH COMPANY, CLINTON, MASS.
Boston New York Chicago San Francisco

THE MIETZ & WEISS **KEROSENE and GAS ENGINE**
Sizes from 1 to 60 H. P.

Send for Catalogue.
burns KEROSENE cheaper and safer than gasoline. Automatic, simple, reliable. No electric battery or flame used. Perfect regulation. Belted or directly coupled to dynamo for electric lighting, charging storage batteries, pumping and all power purposes.
A. MIETZ,
128-138 Mott St., New York.
ADOPTED BY U. S. GOVERNMENT.
Highest Award, direct coupled Generator Set, Paris Exposition, 1900.
Gold Medal, Pan-American Exposition, 1901. Gold Medal, Charleston, S. C., Exposition, 1902.

"CUSHMAN" CHUCKS
All styles and sizes.

Send for Catalogue.
THE CUSHMAN CHUCK CO.,
189 Allyn St., Hartford, Conn.

FOR GUNSMITHS, TOOL MAKERS, EXPERIMENTAL & REPAIR WORK, ETC.
From 9-in. to 13-in. swing. Arranged for Steam or Foot Power, Velocipede or Stand-up Treadle.
Send for Catalogue.
W. F. & JNO. BARNES CO.
Established 1872.
1999 Ruby St., Rockford, Ills.

The Perfection of Pipe Threading
is admitted to be reached when our
No. 9½ PIPE THREADING MACHINE
is used. As a hand machine it is the only one known that will cut and thread an 8 inch pipe with ease and satisfaction. One valuable feature is, that it has no arbitrary lead screw for determining style or pitch of thread to be cut. *Send for Catalogue.*
THE MERRELL MFG. CO.
501 Curtiss St., Toledo, Ohio.

ARTESIAN
Wells, Oil and Gas Wells drilled by contract to any depth from 50 to 3000 feet. We also manufacture and furnish everything required to drill and complete same. Portable Horse Power and Mounted Steam Drilling Machines for 100 to 1200 feet. Write us stating exactly what is required and send for illustrated catalogue. Address
PIERCE WELL ENGINEERING AND SUPPLY CO.
136 Liberty Street, New York, U. S. A.

PALMER
MARINE and STATIONARY
MOTORS
2 and 4 CYCLE



are no experiment, as they are in successful operation in all parts of the world.
Launches in stock.
Send for Catalogue.
PALMER BROS.,
Cos Cob, Conn.

THE B. F. BARNES
WATER EMERY
TOOL GRINDER
Swings a 24x2-inch Wheel.
It has no pump but a simple trough uniquely arranged for supplying water to the Wheel. Easily manipulated and cannot get out of order. Without question it is the most practical and durable wet tool Grinder on the market. Details on request.
B. F. BARNES COMPANY, Rockford, Ill.

The MEDART BOAT BUILDING MATERIALS
bring boat construction within the range of amateurs, at a small cost.
Yachts, Launches, Row Boats.
Send stamp for catalog.
FRED MEDART, 3545 DeKalb St., St. Louis, Mo.

Our Pen Carbon Letter Book Copies Your Letters While you write
Use any pen and your own stationery. If your stationer does not keep it, write for free specimen of work. Beware of infringements. Address Dept. L.
Pen-Carbon Manifold Co., 143-7-9 Centre St., New York.

INDEX OF INVENTIONS

For which Letters Patent of the United States were Issued for the Week Ending

March 10, 1903,

AND EACH BEARING THAT DATE.

[See note at end of list about copies of these patents.]

Abdominal supporter, E. M. Temple	722,644
Account sheet, W. J. Hughes	722,393
Acid, making methylene citric, R. Berendes	722,275
Acid salts and making same, sulfonic, L. O. Helmers	722,506
Acid salts of alkaline earthy metals and metals proper and making same, sulfonic, L. O. Helmers	722,507
Addressing machine, J. W. Underhill	722,268
Aerated waters, apparatus for the automatic production and delivery of, Lee & McMurray	722,368
Air brake, J. Farrar	722,403
Air brake angle cocks, operating device for, W. B. Riley	722,384
Air ship, E. P. Johnston	722,516
Alarm. See Low water alarm.	
Alarm system, electrical, H. M. Sutton et al	722,334
Asphalt, apparatus for treating rock, Downard & Roloson	722,500
Automobile, L. B. Gaylor	722,224
Automobile carriage, W. H. Noyes	722,243
Awning, metallic, E. Cornitius	722,566
Axle box, E. Ottenbacher	722,380
Axle, revolving, C. Faulkner	722,218
Bailing press door closing means, A. Johnson	722,513
Baptismal font, H. F. Nehr	722,242
Barber chair, F. H. Wilsdorf	722,439
Basket, J. I. Lane	722,408
Bath tub, H. Hoeglauer	722,232
Bed, folding, C. P. Brown	722,485
Beet topper and puller, F. Briggs	722,484
Belt, conveyer, H. D. Richards	722,252
Bicycle wheel, G. G. Ritchie	722,435
Bicycle wheel hub, G. Ellstrom	722,402
Binder for sheet music, etc, J. C. Kimsey	722,589
Binder, temporary, W. J. Brown	722,651
Bit stock, I. E. Stump	722,332
Blank ends, machine for finishing, J. H. Haskins	722,300
Boiler, covered plate, C. B. Feather	722,571
Boiler water gage, steam, T. W. Rudd	722,410
Book and binding therefor, N. Bach	722,418
Book, deposit credit, T. D. Taylor	722,391
Book, manifold sales, J. F. Laning	722,593
Book, sample, H. O. S. Carlson	722,283
Boot or shoe fastening, R. Snapper	722,638
Boring bit, extension, J. C. Beyer	722,481
Bottle, J. A. Ames	722,477
Bottle, medicine, C. W. McShane, reissue	12,097
Bottle, siphon, L. Magidson	722,523
Bottle stopper head, G. Limbach	722,596
Bottling apparatus, liquid, G. F. Sumner	722,263
Bowl holder, G. Grimm	722,228
Bowling alley, W. H. Wiggins	722,340
Box lid holder, C. Jack	722,652
Box or package and material therefor, J. H. Greenstreet	722,423
Brake beam fulcrum, F. W. Coolbaugh	722,565
Brake beam reversible fulcrum, C. H. Williams, Jr.	722,655
Brooder, J. H. Swayze	722,437
Brush, fountain, H. Brown	722,281
Buckle, J. P. Hunt	722,511
Buckle, side, J. F. Molloy	722,375
Buildings, etc., moving heavy, H. Sheeler	722,256
Butterin and making same, A. Bergman	722,276
Button, link, E. W. Morehouse	722,529
Button turning machine, H. A. Berger	722,479
Calculating machine keyboard, W. T. Treadway	722,438
Candlestick drip cup, T. M. Mulkerins	722,318
Candy box, C. A. Adams	722,199
Car brake, F. X. Berube	722,201
Car brake, F. Theilengerdes	722,266
Car, convertible, Brill & Haddock	722,280
Car coupling, J. & J. O. Timms	722,267
Car door, grain, J. L. Hamel	722,578
Car door opening or closing device, trolley, W. H. Cook	722,422
Car, hopper bottom, J. M. Hansen	722,209
Car wheel, H. I. McGuire	722,378
Cars on inclines, means for handling cable drawn, T. A. Edison	722,502
Carburetor, gas engine, H. A. Davis	722,357
Carpenter's gage, G. W. Peyton	722,381
Carpet stretcher, C. O. Devilbiss	722,216
Carpet sweeper, J. W. Sykes	722,642
Carrier. See Egg carrier.	
Case. See Traveling case.	
Cash register, F. J. Hull	722,510
Cell cases or egg trays, machine for making, W. B. Sheperd	722,329
Centrifugal separator, Lucas & Jeppson	722,522
Chair attachment, J. F. Bloch	722,482
Check holder and cutter, cash, A. D. Joslin	722,234
Chuck, drill, F. P. Gates	722,575
Cigar maker's knife, O. L. Buehler	722,282
Cigar or cigarette mouthpiece, J. & L. Praedecki	722,383
Circuit controller, J. S. Hobson	722,301
Cleaning smooth surfaces, composition for, M. Peryer	722,454
Clock key, O. C. Eggers	722,280
Cloth cutting machine, R. P. Wright	722,475
Cloth, ornamenting, L. & F. David	722,447
Clutch, F. Claus	722,492
Clutch, friction, F. J. Nutting	722,244
Coal drilling machine, J. W. Shallenberger	722,412
Coat and hat hanger, G. B. Willett	722,548
Cock, check and waste, W. F. Brunt	722,419
Coffee pot, T. C. De Hart	722,213
Coin freed mechanism for gas or other fluid meters, Beale & Bagnall	722,554
Coke drawing machine, B. J. Matteson	722,509
Collar fastener, horse, S. H. Hull	722,304
Comb, C. Moeschl	722,315
Composition of matter, F. Padberg	722,536
Condenser, steam surface, J. R. Richmond	722,628
	722,627
Copy holder, H. L. Massey	722,239
Corn husking machine, F. J. Fitzpatrick	722,448
Corn shocker shock forming post, B. R. Benjamin	722,397
Corn shredding and husking machine, W. B. Martindale	722,429
Couch head rest support, J. Luppino	722,372
Cultivator, C. L. Swanson	722,264
Cultivator, J. McCoy	722,319
Cultivator coupling, R. W. E. Hayes	722,231
Cultivator, two row disk, L. Kirlin	722,235
Culvert, F. S. & F. H. Beach	722,396
Curtain ring, J. W. Leslie	722,370
Cut off for cisterns, automatic, Deming & Tully	722,214
Cuttlebone mold, A. A. Geiger et al	722,361
Disinfecting apparatus, E. Fournier	722,503
Display mechanism, curtain, A. M. Davy	722,568
Display rack, C. E. Brackbill	722,279
Distance meter or range finder, J. P. Sorensen	722,435
Dividers, H. C. Adamson	722,551
Door, electrically operating, J. Chambers, Jr.	722,446
Double claw or grip device, H. Sheeler	722,257
Dough cutter or slicer, E. P. Mossmer	722,452
Dough dividing machine, F. H. Van Houten	722,545
Draft equaliser, P. Yeager	722,347
Dredging machine, W. W. Lea	722,595
Dress shield, D. Basch	722,395
Drill. See Grain and fertilizer drill.	
Driving mechanism, W. Scott	722,388
Driving wheel, traction motor, E. Boniecki	722,278
Drop curtain, mirror, H. M. Williams	722,342
Duplicating machine, H. C. Gammeter	722,404
Dye and making same, yellow sulfur, Ris & Mylius	722,630
Dynamos, automatic regulator for constant current, F. B. O'Hanlon	722,533
Egg carrier, H. S. Jenne	722,512
Electric controller, F. A. Merrick	722,527
Electric current controller, J. J. Murphy	722,453
Electric furnace, A. A. Shade	722,411

(Continued on page 215)

Young men and women in search of Permanent, Profitable Employment, will appreciate our new, easy method of selling
ALUMINUM COOKING UTENSILS

Takes away all objectionable features of canvassing and adds greatly to the profit. Over 100 different utensils. Very highest grade. Do not burn food. Cannot rust, crack or scale. Last a lifetime.
Write to-day for our plan. It's the best thing you ever saw.
The Aluminum Cooking Utensil Co.
District 5, Pittsburgh, Pa.

"HENDRYX"



It's a Guarantee of Quality
2,000,000 Sold in 12 Years
EVERY REEL WARRANTED
Booklets mailed free
The Andrew B. Hendryx Co.
New Haven, Conn., U. S. A.

THE BRIGHT WHITE LIGHT FOR
MAGIC LANTERNS
Also for Bromide Enlarging, Copying, Photo-Engraving, intensely brilliant, very portable, burns kerosene, costs 1 cent per hour. Send for copy Franklin Institute award and lists of Stereopticons, Moving Pictures and Slides.
WILLIAMS, BROWN & EARLE,
Dept. 6. 918 Chestnut St., Philadelphia.

Self Supplied Moisture
FREE FOR 30 DAYS.
We will send our grand new book "HOW TO MAKE MONEY WITH POULTRY AND INCUBATORS" free, postpaid, for the next 30 days to all who mention this paper in writing for it. It's the best we ever published. 8x11 ins. 196 pages. Handsome original illustrations. 12 special chapters on vital poultry subjects. Write to our nearest office for it.
Cyphers Incubator Co.,
Buffalo, N. Y., Chicago, Ill., Boston, Mass., New York, N. Y.

MATCH FACTORY.—DESCRIPTION of an English factory. SCIENTIFIC AMERICAN SUPPLEMENT 1113. Price 10 cents. For sale by Munn & Co. and all newsdealers.

WELL DRILLING Machines
Over 70 sizes and styles, for drilling either deep or shallow wells in any kind of soil or rock. Mounted on wheels or on sills. With engines or horse powers. Strong, simple and durable. Any mechanic can operate them easily. Send for catalog.
WILLIAMS BROS., Ithaca, N. Y.

YOU ARE EASY
If you need a carpenter to help you repair your roof with
Warren's Natural Asphalt Stone Surfaced Roofing

Has 9 inch lap edge.
The best and most serviceable prepared roofing on the market. It is durable, fire-proof, and does not require painting. Comes ready to lay in rolls containing 108 sq. ft.
Warren Chemical & Mfg. Co., 172 Broadway, New York

KNOWING HOW Gas Engines should be made and making them to conform to our own high standard gives the
OLDS Gas & Gasoline Engine
a prestige which has been confirmed by the test of 23 years' hard use. Reliable, Economical and Durable. Stationary Engines, 1 to 80 h. p. Portable Engines, 4½, 8 and 12 h. p.
Write for catalogue.



OLDS MOTOR WORKS, 216 River St., Lansing, Mich.

THE WATERBURY
Emery Grinder,
with adjustable table, for flat surface grinding and finishing, and for ordinary tool grinding.
Send for Catalogue.
BLAKE & JOHNSON
P. O. BOX 7,
WATERBURY, CONN.

FOR TOWN OR COUNTRY USE
There is no more serviceable or simple engine than the WEBER JUNIOR a 2½ H. P. engine suitable for grinding feed, pumping water, shelling corn, &c., or for running fans, presses, churns, butchers' machinery, sheep shearing machines, etc. Complete with water and gasoline tanks and pipes. Oilers, etc., all ready for business. Heavy balance wheels. One operating valve. 650 lbs.

Floor space, 24x72 ins. Speed,375 rev.
Weber Gas & Gasoline Engine Co.
Box 1114, Kansas City, Mo.

THE AMERICAN THERMO-CALL BUTTON
discovers and reports fire automatically. Can be attached to the existing wires in hotels and manufacturing plants. Invaluable as a life and property saver in residences. No possible chance for fire to secure headway without sounding alarm. Permanent, not fusible.
American Thermo-Call Co., Boston, Mass.
Mfrs. of thermostatic devices of all kinds

Universal Safety Tread
Made to walk on with perfect safety.

Steel, Brass, and Manganese Bronze.
Stairs, Coal Holes, Car Steps, Etc.
For Elevators or wherever you walk is always secured by its use.
UNIVERSAL SAFETY TREAD CO., 45 Broadway, NewYork

D. L. HOLDEN
REAL ESTATE TRUST BLDG. PHILA. PA.
SOLE MANUFACTURER
REGEALED ICE MACHINES
SEE FIRST PAGE SCIENTIFIC AMERICAN SEPT. 2. 1899

Power and Control

These essentials of the serviceable and safe automobile are developed in the Cadillac Automobile through new principles of engineering and perfect mechanical construction. The engine is very compact and very powerful; the transmission gear a triumph of mechanics; the steering wheel very sensitive—and absolute in its control; the brakes reliable under all conditions of grade and speed; running gear and body strong, but graceful. The

CADILLAC

is The Automobile that Solves the Problem

of safe and rapid transit on all roads, under all conditions. If you know of an auto fault you'll find it corrected in the Cadillac. Price $750. Detachable tonneau, at an extra cost of $100, converts this graceful runabout for two into a delightful touring car for four.

Our free illustrated booklet N gives address of agency nearest you where the Cadillac may be seen.

CADILLAC AUTOMOBILE COMPANY, Detroit, Mich.

Squabs Pay Best Hens

Easier, need attention only part of time, bring big prices. Raised in one month. Attractive for poultrymen, farmers, women. Send for FREE BOOKLET and learn this *immensely rich home industry.*

Plymouth Rock Squab Co., 14 Friend St., Boston, Mass.

HANDS DIRTY?

Gre-Solvent instantly dissolves and removes machine grease, paint and ink. **Miles ahead of soap.** Harmless. Antiseptic. By mail, prepaid, 15c. and 25c., stamps. Sample free to dealers. Correspondence solicited.

THE UTILITY CO., 233 Greenwich St., New York.

The Test

of Service

always proves the absolute supremacy of the

Remington

Typewriter

Remington Typewriter Company
327 Broadway, New York

Electric motor regulation system, P. J. Collins	722,563
Electric time switch, H. C. Froelich	722,292
Electrical contact brush and producing same, H. N. Motsinger	722,606
Electrode for electrolytic apparatus, secondary, P. Imhoff	722,583
Elevator, W. L. Holman	722,364
Elevator gate operating device, C. W. Kirsch	722,500
Embankment protector, E. M. Boynton	722,445
Engine, F. H. Sleeper	722,259
Engine reversing gear, Fairbanks & Sauer	722,217
Evaporating pan, E. R. Shaw	722,436
Exercising apparatus, F. D. Smith	722,462
Exhaust silencer, M. Crawford	722,567
Extensible round top table, E. B. Gregory	722,577
Eyeglasses, E. L. Lembke	722,521
Fabrics, manufacturing, A. Oesterheld	722,246
Fall rope carrier and operating device therefor, Lambert & Delaney	722,518
Fan, electric, R. P. Chandler	722,208
Feed for boilers, automatic water, C. Wilkins	722,549
Feed water for motor vehicles, heating, W. J. and G. Lane	722,309
Fence post, Wherry & Hill	722,474
Fence post, W. E. Owens	722,615
Fertilizer feeder, Miner & West	722,528
Fibrous plants, machine for defibrating, W. S. Belding	722,556
Figure, mechanical, C. W. Chafee	722,207
Filter, G. F. Hodkinson	722,581
Filter, F. Rothe	722,632
Filter, barrel, H. R. Cassel	722,590
Fire escape, E. Anderson	722,552
Fire escape, Wood & Boyse	722,648
Fireproof construction, G. A. Schillinger	722,460
Fluid compression, apparatus for elastic, H. Bland	722,558
Fruit box extension frame, J. Nicholas	722,534
Fruit harvester, G. H. Shellaberger	722,413
Fulling machine, L. P. Hemmer	722,363
Game apparatus, A. J. Musselman	722,247
Game apparatus, C. A. Fowler	722,359
Game apparatus, C. N. Morgan	722,603
Garment clasp, O. Kemper	722,308
Garment clasp or hose supporter, A. H. Cohn	722,285
Garter, P. S. Bauer	722,274
Gas burner, C. F. Glocker	722,220
Gas meter, H. H. Sprague	722,390
Gas or gasolene engine, B. Garlius	722,223
Gas regulating valve, automatic, Holley & Rix	722,302
Gate, L. Doerr	722,358
Glass blowing machine, J. Schies	722,634
Glass bodies, manufacturing hollow, O. Schott	722,386
Gold from cyanic solutions, precipitating, A. Prister	722,455
Governor, R. Conrader	722,564
Grain and fertilizer drill, F. N. Isham	722,407
Graphite separator, J. H. Davis	722,211
Grazing stake, J. R. McGoron	722,531
Hair fastener, W. A. Sloan	722,260
Hammer, pneumatic, Oldham & Padbury	722,614
Harp, W. Moerscher	722,602
Harrow, J. H. Davis	722,287
Harrow and cultivator, combined, S. R. Stewart	722,261
Harvester, corn, A. S. Gove	722,227
Harvester, corn, W. W. Burson	722,487
Harvester, cotton, A. Campbell	722,421
Harvester, pea, F. W. Rapson	722,326
Hasp, R. D. Wirt	722,344
Header platform, Campbell & C. H. Schwartz	722,488
Heating furnace and boiler, steam, G. A. Copp	722,493
Heating systems, means for regulating the temperature in, W. P. Powers	722,251
Hedge trimmer, W. Linhoff	722,371
Heel, boot or shoe, J. L. Izan	722,307
Hinge, detachable, G. B. Pickop	722,624
Hog snout holder, G. F. Snider	722,434
Hoisting apparatus, A. E. Norris	722,613
Horseshoe, T. A. McKay	722,610
Horseshoe, elastic tread, H. D. Traveller	722,337
Hydrocarbon burner, J. G. Branch	722,202
Hydrocarbon motor, J. W. Packard	722,431
Hypodermic needle, C. D. Brooke	722,203
Igniting device, electric, F. Sturm	722,333
Indicator. See Liquid level indicator.	
Internal combustion engine, Riotte & Radcliffe	722,629
Intestine cleaner, F. Matheyer	722,525
Iron and steel, cleansing and improving the quality of, F. C. Weber	722,270
Iron from its ore, reducing, M. Ruthenburg	722,255
Journal bearing, A. M. Kerr	722,254
Journal bearing, E. J. Decker	722,427
Journal bearing shell, M. J. Rogers	722,495
Journal bearing shell, M. J. Rogers	722,327
Keg or cask cooler, S. M. J. House	722,509
Ladder, step, A. E. Paskell	722,409
Lamp, gas, A. H. Humphrey	722,306
Lamp socket, D. A. Schutt, reissue	12,099
Lamp, vapor burning, W. Mitchell	722,601
Lamps, gas-detecting attachment for miners' safety, Beard & Mackie	722,555
Leather staking machine, Slocomb & Craig	722,461
Letter box, B. W. Parker	722,323
Letter, sign, B. V. Kostka	722,592
Lift, tradesman's, C. A. Bouck	722,442
Linotype machine, L. Cesana	722,284
Linotype machine, G. A. Bates	722,353, 722,645
Liquid level indicator, Tripp & Wadleigh	722,645
Lock, A. D. Plowden	722,325
Lock, E. Heidman	722,406
Lock, B. Phelps	722,619 to 722,623
Locks having rocking chambers, construction of, L. de Freville	722,537
Locomotive cab ventilator, K. Rushton	722,539
Locomotive engine, F. J. Cole	722,356
Loom, power, S. F. Patterson	722,248
Low water alarm, steam boiler, F. O. Stanley	722,330
Lubricating mechanism, N. A. Christensen	722,209
Malt for mashing, apparatus for preparing bruised or ground, V. Lapp	722,310
Match machine, E. B. Stocking	722,331
Mausoleums, vaults, etc, roof for, C. E. Taynton	722,392
Medical use, electrical generator and distributer for, E. L. Madden	722,598
Metal post, G. Schneider	722,635
Metal sheet drying and fluxing machine, J. C. Taliaferro	722,643
Milk, regenerative apparatus for the simultaneous warming and cooling of, L. P. Larsen	722,306
Mold and core drying apparatus, W. L. Mars	722,312
Motor. See Hydrocarbon motor.	
Motor, C. H. Roth	722,328
Music record, diagram, or pattern, R. A. Gally	722,574
Musical instrument mechanical playing attachment, E. D. Ackerman	722,476
Necktie, combination, Samter & Pinner	722,633
Nigger bar cushion device, McGregor & Somers	722,320
Nipple, teething, F. B. Anderson	722,350
Nut lock, W. C. Stickel	722,640
Nut lock, M. Bartley	722,649
Oil burner, J. McDermott	722,539
Ore handling plant, G. H. Hulett	722,420
Packing, metallic, G. C. Walters	722,269
Packing ring box, L. H. Martell	722,428
Packing tube, G. H. Brownell	722,204
Painter's appliance, L. W. Young	722,349
Paper watermarking device, J. Barnett	722,553
Peat, manufacturing plastic objects from, N. Reif	722,626
Pen filler, reservoir fountain, M. T. Horn	722,508
Penholders, device for mounting, F. McIntyre	722,609
Pencil sharpening machine, D. H. Rogan	722,631
Phonograph repeating attachment, D. Petri-Palmedo	722,616
Photographic emulsion and making same, H. Luttke	722,238
Photographic shutter, L. J. R. Hobet	722,449
Pick, S. Jones	722,586
Picture apparatus, animated, J. A. Pross	722,382
Picture hanger, A. W. Magerhans	722,311
Picture hanging device, W. F. Towne	722,467
Picture machine, moving, W. P. Warren	722,393
Pie filler, soft, J. J. Connors	722,210
Pile, E. Villet-Carter	722,417
Pipes, floor plate for steam and water, A. R. Wells	722,338

(Continued on page 216)

Dueber-Hampden Solid Gold Watch Cases

are not only handsomer and more durable, but **stronger and better** than any alloy or combination of metals can be.

DUEBER 18 K — These are the Trade Marks — 14 K DUEBER

"ACCURATE TO THE SECOND"

Dueber-Hampden Watches

are made in our factories, the most complete watch factories in the world. We make the entire watch, both movement and case, and guarantee them.

Wm Kinsley — 21 jewels, 17 jewels. For Men.

"The 400" Smallest, daintiest Women's watch.

Send for free book "Guide to Watch Buyers."

Dueber-Hampden Watch Works
56 South Street, Canton, Ohio

FAY & BOWEN Motors & Launches



Operated by Gasoline Vapor Motors 1½ to 25 H.P.

THE FAY & BOWEN MARINE MOTOR is a revelation to those who have used others. Reliable, safe, durable and easy to operate. Remarkable speed control. Best of all, it starts when you start it. No handle or crank is used. Our patented igniter is absolutely unique and always instant and positive in action. It is really the only perfect and satisfactory igniter.

Motors complete from 1½ to 25 h. p. ready for installation. We also build handsome launches with motors installed and ready to run. SEND FOR CATALOGUE.

FAY & BOWEN, 55 Mill St., Auburn, N. Y.

MORAN FLEXIBLE JOINT

for Steam, Air or Liquids. Made in all sizes to stand any desired pressure.

Moran Flexible Steam Joint Co., Inc'd, 149 3d East St., LOUISVILLE, KY.

1 Gallon in 4 Minutes

of the purest drinking water and free from all solid atoms and disease germs. Every household should have a

BERKEFELD FILTER

which prevents the spread of many diseases generally originating in impure water.

BERKEFELD FILTER CO., 4 Cedar Street, New York.

ELECTRO MOTOR, SIMPLE, HOW TO make.—By G. M. Hopkins. Description of a small electric motor devised and constructed with a view to assisting amateurs to make a motor which might be driven with advantage by a current derived from a battery, and which would have sufficient power to operate a foot lathe or any machine requiring not over one man power. With 11 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 644. Price 10 cents. To be had at this office and from all newsdealers.

ELECTRICAL TESTING

If you wish to know the properties of any electrical instruments, materials or apparatus, the utility of an invention or the practicability of an idea, tests by us might be of great value to you.

NEW YORK LABORATORY LAMP TESTING BUREAU
8th Floor. No. 14 Jay Street, New York

COLD GALVANIZING

Save all the Spelter consumed in galvanizing by the hot process by using our Patent Cold Galvanizing Process, as the amount of spelter lost as dross in the hot process if used in our process will give sufficient protection to any kind of work to make it rust-proof even against salt air and sea water. Our Patent Process is now in use all over the country. Our licensees include **U. S. Government, The Standard Oil Co., Herreshoff Boat Building Co., Townsend & Downey, Armour Packing Co.** Licenses granted on royalty basis. Sample and custom work done at our factory, 108-110 W. 11th St. Main Office, 346 Broadway. **U. S. ELECTRO-GALVANIZING CO.**

We manufacture gears and bodies suitable for all purposes. We also sell supplies and can furnish any part or all the parts for a gasoline or steam rig. See our late catalogue, FREE.

NEUSTADT-PERRY CO., 926-930 S. 18th St., St. Louis, Mo.

CHAS. T. HOWE & Co., 51 Hudson St., New York, Export Agents.

FREE! Just what every young electrician wants. Lights lamps, runs motors, will decompose water and a thousand wonderful things. Most complete little generator made. Runs off a sewing machine. Send stamp for particulars.

C. & T. Elec. Co., Department H, Syracuse, N. Y.

Midget Dynamo or Motor.

Little Wonder TELEPHONE FOR $6.00

We will send 2 telephones, 200 feet of wire, and all necessary staples, with full instructions how to put them up and operate.

HIPWELL MFG. CO., Allegheny, Pa.

Gas Engine IGNITER

Complete with spark coil, $12.00. The **Best Thing** on the market. Latest and most improved model.

Send for Circular.

Carlisle & Finch Co., 233 E. Clifton Av., Cincinnati, O.

The STEFFEY Motor-Cycle IS THE BEST.

We also have a complete line of **Motors, Castings & Accessories** for Bicycle Automobile, or Marine. Highest grade. We undersell all others. 2-cent stamp goes our catalogues.

STEFFEY Mfg. Co. 2730 Brown Street, Philadelphia, Pa.

"OIMA" Liquid Pistol

Durable and Safe

5 inches long

Made of Steel, Nickel Plated

Will stop the most vicious dog (or man) without permanent injury. Valuable to bicyclists, unescorted ladies, cashiers, horses, etc. **Loads from any liquid. No cartridges required. Over 200 shots in one loading.** All dealers, or by mail, 50c.

PARKER, STEARNS & SUTTON, 226 South St., New York

Howard Two and Four Cycle MARINE AND AUTOMOBILE MOTORS

Write for Cat.

Grant Ferris Co. Troy, N. Y.

Shipped On Approval

We will ship any bicycle C.O.D. on approval *without a cent deposit* and if accepted allow **10 DAYS FREE TRIAL** before purchase is binding.

New 1903 Models

"Bellise,"	complete	$8.75
"Cossack,"	Guaranteed High Grade	$10.75
"Siberian,"	a beauty	$12.75
"Neudorf,"	Road Racer	$14.75

no better bicycles at any price.

Any other make or model you want at one-third usual price. Choice of any standard tires and best equipment on all our bicycles. *Strongest guarantee.*

RIDER AGENTS WANTED in every town to buy a sample wheel at *special price* and take orders for our improved '03 models. *There's big money in it.*

Good 2nd-hand Wheels $3 to $8.

DO NOT BUY a bicycle until you have written for our free catalog with large photographic engravings and full descriptions.

MEAD CYCLE CO. Dept. 59-C, Chicago.



Oldest Incorporated Co.

in the U. S. making

AUTOMOBILE BOILERS

Low Water Alarms — Reducing Valves
Damper Regulators — Steam Traps

Cannon made a Record Mile in 1.05 1-5 with our 34-inch boiler. *Write for Catalogue.*

Steam Carriage Boiler Co.
119 W. 1st St., Oswego, N. Y.

"When One Man Equals Ten"

in the quantity and quality of his work there must be a saving of **90** per cent. That is the great economical characteristic in

Hook's Pneumatic Coating Machine

which paints or whitewashes ten times the superficial area that any painter could cover with a brush in a given time. It gives any surface an evener and more durable coating and is far cleaner than brush work with infinitely less labor and trouble. With this machine we have put **"STAY-THERE" PAINT** on nearly everything from an Ocean Liner to a Row Boat, from a Grain Elevator to a Corn Crib.

"STAY-THERE" PAINT

is a new chemical substitute for oil-paint at one-fifth its cost. It is weather-proof and fire-proof. Made in white, black, and 24 colors. Circulars, folders, and booklets free, with price-list, on application to

F. E. HOOK, Manufacturer,
11 to 27 HOOK BUILDING, HUDSON, MICH., U. S. A.

Valuable Books!

NOW READY.

Modern Machine Shop Tools

Their Construction, Operation and Manipulation, Including Both Hand and Machine Tools.

By W. H. VANDERVOORT, M. E.

Large 8vo. 526 Pages. 673 Illustrations. Bound in Cloth.

Price $4.00.

An entirely new and fully illustrated work, treating the subject of **Modern Machine Shop Tools** in a concise and comprehensive manner. Special care has been taken to eliminate all matter not strictly pertaining to the subject, thus making it possible to give the reader complete information pertaining to machine shop tools and methods in a single volume at a moderate price.

The work is logically arranged; the various hand and machine tools being grouped into classes, and description of each is given in proportion to their relative importance. The illustrations represent the very latest tools and methods, all of which are clearly described. Each tool is considered from the following points:
FIRST—Its construction, with hints as to its manufacture.
SECOND—Its operation, proper manipulation and care.
THIRD—Numerous examples of work performed.

TWENTY-THIRD EDITION

Experimental Science

By GEORGE M. HOPKINS

Revised and Greatly Enlarged. 2 Octavo Volumes. 1,100 Pages. 900 Illustrations. Cloth Bound, Postpaid, $5.00. Half Morocco, Postpaid, $7.00. Or Volumes Sold Separately: Cloth, $2.50 per Volume; Half Morocco, $3.00 per Volume.

EXPERIMENTAL SCIENCE is so well known to many of our readers that it is hardly necessary now to give a description of this work. Mr. Hopkins decided some months ago that it would be necessary to prepare a new edition of this work in order that the many wonderful discoveries of modern times might be fully described in its pages. Since the last edition was published, wonderful developments in wireless telegraphy, for example, have been made. It was necessary, therefore, that a good deal of new matter should be added to the work in order to make it thoroughly up-to-date, and with this object in view some 200 pages have been added. On account of the increased size of the work, it has been necessary to divide it into two volumes, handsomely bound in buckram.

DIES

THEIR CONSTRUCTION AND USE

For the Modern Working of Sheet Metals.

By JOSEPH V. WOODWORTH

Octavo. Cloth. Very Fully Illustrated.

Price $3.00 Postpaid.

This book is a complete treatise on the subject and the most comprehensive and exhaustive one in existence. A book written by a practical man for practical men, and one that no diemaker, machinist, toolmaker or metal-working mechanic can afford to be without.

Dies, press fixtures and devices from the simplest to the most intricate in modern use, are shown, and their construction and use described in a clear, practical manner, so that all grades of metal-working mechanics will be able to understand thoroughly how to design, construct and use them, for the production of the endless variety of sheet-metal articles now in daily use.

REVISED and ENLARGED EDITION

The Scientific American

Cyclopedia

Of Receipts, Notes and Queries.

15,000 Receipts. 734 Pages.

Price, $5.00 in Cloth. $6.00 in Sheep. $6.50 in Half Morocco. Post Free.

This work has been revised and enlarged,

900 New Formulas.

The work is so arranged as to be of use not only to the specialist, but to the general reader. It should have a place in every home and workshop. A circular containing full **Table of Contents** will be sent on application.

Those who already have the Cyclopedia may obtian the

1901 APPENDIX.

Price, bound in cloth, $1.00 postpaid.

JUST PUBLISHED

HARDENING, TEMPERING, ANNEALING and FORGING OF STEEL

By JOSEPH V. WOODWORTH

Author of "DIES, Their Construction and Use."

Octavo. 200 pages. 200 Illustrations. Bound in Cloth.

PRICE, $2.50

A new work from cover to cover, treating in a clear, concise manner all modern processes for the **Heating, Annealing, Forging, Welding, Hardening and Tempering** of steel, making it a book of great practical value to metal-working mechanics in general, with special directions for the successful hardening and tempering of all steel tools used in the arts, including milling cutters, taps, thread dies, reamers, both solid and shell, hollow mills, punches and dies, and all kinds of sheet metal working tools, shear blades, saws, fine cutlery, and metal cutting tools of all description, as well as for all implements of steel, both large and small. In this work the simplest and most satisfactory hardening and tempering processes are given.

Full descriptive circulars of above books will be mailed free upon application.

MUNN & CO., Publishers,
361 BROADWAY NEW YORK.

Piston ring, W. G. Wilson	722,440
Planter, combined check row and drill, A. Anderson	722,442
Planter, cotton, I. H. Jackson	722,293
Plow, wheel, Buchanan & Hickman	722,265
Pneumatic despatch tube apparatus carrier, C. H. Burton	722,562
Pneumatic lock, J. Sines	722,258
Pocket book, H. J. Gutsman....722,283 to	722,295
Pocket, safety, B. A. James	722,584
Polishing truck, tilting table, L. Gassard	722,296
Power transmitting device, F. Claus	722,491
Printing, Kittredge & Niemes	722,591
Propeller, screw, J. A. Fehlman	722,572
Pump lifter, T. D. Stark	722,463
Pump mechanism, Ruch & Baker	722,385
Pump, multiple cylinder, W. H. Millspaugh	722,240
Pump pressure regulating device, R. Birkholz	722,443
Pump, sand, C. M. Hester	722,424
Pump suction valve, J. Klein, reissue	12,094
Pump, vacuum, J. Stumpf	722,416
Punch and nail set, screw center, N. Bond	722,559
Radiator, portable, J. M. Cripe	722,286
Rail clamp, swinging, J. F. Busey	722,420
Rail joint, A. Russell	722,538
Railway, carriage, H. L. Stillman	722,641
Railway cross tie, F. W. Dunnell	722,501
Railway rail joint, H. C. Wortman	722,346
Railway rail joint, Runolfson & Johnson	722,457
Railway tie, Alfred & Chipman	722,200
Railway tie, W. A. Wetmore	722,473
Railway tie, metallic, G. H. Lyle	722,373
Railway train safety appliance, R. Wittmann	722,646
Range, gas, G. A. Simpson	722,414
Ratchet wrench, A. P. Kershner	722,450
Refuse burner, D. B. Donnelly	722,289
Revolving press, Hough & Gary	722,582
Riveter or punch, field pressure, R. S. Caskey	722,480
Roller rack, J. F. Johnson	722,514
Rolling flanged sections, T. Morrison	722,605
Rotary engine, H. Bergmann	722,480
Rotary engine, W. Buckingham	722,560
Ruler, dressmaker's, S. S. Freeman	722,221
Safety pin and hook, combined, W. F. Peet	722,617
Sash attachment, window, P. Mayotte	722,526
Saw, wabble, C. Seymour	722,541
Sawing machine, J. R. Thomas	722,335
Scaffold, adjustable, Donecker & Nagle	722,498
Scale, bracket, G. E. Miller	722,374
Scale frames, blank for sheet metal, W. N. Pelouze	722,618
Scraper, F. T. Powell	722,250
Screen. See Window screen.	
Seal design, apparatus for melting sealing wax, etc., on paper or other surfaces for the production of ornamental, C. H. Williams	722,341
Sewing machine, Dimond & Dial	722,496
Sewing machine creasing means, G. H. Dimond et al	722,497
Sewing machine loop holder, H. A. Klumm	722,236
Sewing machine presser foot, R. G. Woodward 722,441, 722,550,	722,647
Shade bracket, window, J. A. Scott	722,387
Shear table, B. P. Swyers	722,265
Shearing or clipping cutters, T. A. Martin	722,313
Shirt waist holder and skirt supporter, F. E. Moody	722,316
Shoe stretching device, J. Karlson	722,517
Show case corner or fastening, O. C. Kade	722,588
Smoke stack, P. Dickinson	722,288
Smoking pipe, B. Ganim	722,365
Solder, Nelid & Campbell	722,473
Sound record, T. H. Macdonald, reissue	12,096
Sound records, making, T. H. Macdonald, reissue	12,095
Speed changing and reversing mechanism, A. C. Sargent	722,458
Speed indicator, vehicle, A. L. McMurtry	722,532
Speed transmission mechanism, variable, F. J. Nutting	722,245
Spoke, wheel spring, A. Prouvost	722,432
Stacker, pneumatic, C. N. Leonard	722,369
Stackers, means for operating the adjustable hoods of pneumatic straw, J. A. Moser	722,451
Stanchion, L. H. Andersson	722,271
Stanchion, cattle, L. Garrett	722,300
Stand for umbrellas, canes, etc., H. Werle	722,546
Steam boiler, F. Belway	722,415
Steam engine, B. J. Carter	722,206
Steam engine, P. Gindt	722,225
Steam generator, J. W. Sutton	722,466
Steam generator, smokeless, O. D. Orvis	722,321
Steam separator, W. J. Baker	722,272
Steam trap, J. L. Chapman	722,400
Steam trap, G. S. Rahmeyer	722,650
Steel, C. H. Halcomb	722,504
Steel dies, manufacture of, Ball & Nock	722,351
Stoker, steam, E. B. Valentine	722,471
Stone, manufacture of artificial, C. W. Stevens	722,464
Stool, bookkeeper's, R. W. Jennison	722,585
Storage apparatus, A. C. Johnston	722,515
Stovepipe polishing machine, I. Gottfield	722,297
Stovepipe thimble, A. Muellerweiss	722,607
Stretcher, J. E. Reeves	722,456
Stud, Schlieper & Steinbock	722,540
Stuffing box, B. P. Fielden	722,219
Subway construction, J. and D. W. Ohaver	722,247
Suit, combination, M. E. Cavanaugh	722,490
Surgical instrument, N. J. Smedley	722,542
Surgical or similar purposes, electrical instrument for, M. D. Law	722,594
Synchronism indicator, J. E. Woodbridge	722,345
Table lock, pedestal extension, E. Tyden 722,469,	722,470
Table locking device, pedestal extension, E. Tyden	722,468
Tank discharge means, L. H. Mitchell	722,314
Tar extract, obtaining, M. C. M. Tixier	722,336
Target, C. L. Finney	722,220
Telephone circuit, subscriber's, W. W. Dean	722,212
Telephone support, J. S. Young	722,348
Telephone system, Lattig & Goodrum	722,367
Telephone system, lock out party line, Goodrum & Lattig	722,362
Tenoning machine, Hayes & Kuebler	722,230
Theater scenery, apparatus for raising or lowering, E. Lytton	722,597
Thill coupling, J. Cummings	722,401
Tie. See Necktie.	
Tile carb, F. Hill	722,580
Tile flooring, C. P. Lawshe	722,520
Tile or brick, hollow, O. C. Pixley	722,249
Tire bolt wrench, D. Smith	722,637
Tire, pneumatic, J. G. Moomy....722,376,	722,377
Tire, pneumatic, E. Midgley	722,600
Tire protecting band, pneumatic, J. Wheeldon	722,339
Tire, road vehicle, R. Nadall	722,612
Tire, vehicle, O. Schaefer	722,650
Tobacco pipe, H. M. Willis	722,343
Tobacco pipe, A. W. Thornton	722,543
Tools to sockets, means for connecting, A. F. Pitkin	722,324
Trace carrier, F. L. Beymer	722,277
Traction device, electrical, W. W. O'Malley	722,255
Train robberies, device for preventing, G. A. Copp	722,494
Tramway, aerial, J. N. Bellwald	722,557
Traveling case, W. A. Moody	722,317
Traveling case, C. S. Morris	722,604
Tricycle, W. A. Marquis	722,524
Trolley, electric railway, B. L. McCartney	722,608
Trolley pole, H. P. Oller	722,570
Trolley, trackless, A. B. Upham	722,654
Trolley wagon, G. H. Hulett	722,426
Truck and skid, combined, J. E. Dilger	722,570
Truck for transport of ships, etc., Suppan & Szendi	722,456
Truck frame, railway car, J. M. Hansen	722,298
Truck, portable, J. E. Dilger	722,569
Tubes, manufacturing conical, E. Bock	722,398
Turning machine, wood, L. D. Bullock	722,486
Typewriter, A. C. Ferguson	722,291
Typewriting machine, G. Podlich	722,625
Typewriting machine copy holder, H. L. Lanphear	722,363
Umbrella, C. S. Gurney	722,229
Umbrella drip cup, P. J. Flynn	722,573
Vacuum pan, J. Lang et al	722,519
Valve, F. Palm	722,322
Valve and igniter, combined exhaust, J. Tracy	722,544
Valve dressing tool, J. T. Fuhrmann	722,222
Valve, reducing, P. B. Cain	722,358

(Continued on page 217)

"To Err is Human"—
Not to Err—Elgin.

The man who is always right on time is the man who carries the

ELGIN WATCH

Every Elgin Watch is fully guaranteed. All jewelers have Elgin Watches. "Timemakers and Timekeepers," an illustrated history of the watch, sent free upon request to

ELGIN NATIONAL WATCH CO., ELGIN, ILL.

We Are Manufacturers of Complete Outfits for

PROSPECTORS, EXPLORERS, CAMPERS, CANOEISTS, FISHERMEN and SPORTSMEN

Whether you camp in the Polar Circles or in the Tropics, we can supply you with a suitable equipment, and give you expert advice on its use.

Our 1903 Catalogue contains 160 illustrated pages of camp necessities, comforts and conveniences. It is worth a quarter, but will be sent free to readers of the SCIENTIFIC AMERICAN sending for same to dept. F.

ABERCROMBIE & FITCH,
314-316 Broadway, New York City.

BARKER MOTORS

1 to 8 H. P., $80 to $220

Have more good points, fewer parts and require less attention in operation than any other.

Launches, Valves, Specialties.

C. L. Barker, Norwalk, Ct.

A BOON IN BRAKE BLOCKS.

The acknowledged leader in its line is **Potter's Spring Brake Block** for efficiency, durability, economy, strength and serviceability. In use by builders of the highest grade carriages and wagons. **Morgan Potter,** Fishkill-on-Hudson, N. Y., U. S. A.

MAXIMUM LIGHT — MINIMUM COST

The "BEST" LIGHT

Is a portable 100 candle power light, costing only 2 cts. per week. Makes and burns its own gas. Brighter than electricity or acetylene, and cheaper than kerosene. **No Dirt. No Grease. No Odor.** Over 100 styles. Lighted instantly with a match. Every lamp warranted.

Agents Wanted Everywhere.

THE "BEST" LIGHT CO.
81 E. 8th St., CANTON, OHIO.

OWNERS OF ORIGINAL PATENTS



CRAMER

Crown Plates are more rapid than any other plate in the market With this plate clear quick printing Negatives can be secured

These plates are especially adapted for Tourists using Hand-Cameras

G. CRAMER DRY PLATE CO.

ST. LOUIS, MO.

Offices in

New York: 32 East 10th Street
Chicago: 1211 Masonic Temple
San Francisco: 819 Market Street

MECHANICALLY TRUE.

Our machinery for correctly shaping and spacing the teeth of all kinds of gear is assuring work that is mechanically perfect. Cost much less than on the old principle Send for free booklet. BUFFALO GEAR & PATTERN WORKS, Buffalo, N. Y.

BABBITT METALS.—SIX IMPORTANT formulas. SCIENTIFIC AMERICAN SUPPLEMENT 1123. Price 10 cents. For sale by Munn & Co. and all newsdealers. Send for catalogue.

The Franklin Gas Engine

One-Half Horse Power

worth $100 complete. We sell all necessary castings, materials and detail drawings for $16.50. For real work—not a toy 450 revolutions per minute. Upright or horizontal form. Finished parts sold separately. Runs by gas or gasolene. For boys and men with a mechanical turn. Write for circular 9.

PARSELL & WEED,
129-131 West 31st St., New York.

How to Paint a House Cheap

And Have it Guaranteed to Look Better, Wear Longer and Cost Less Than the Best White Lead Paints.

Never Fades, Cracks, Chalks, Peels or Blisters and is Not Affected by Gases. Fifty Sample Colors and Illustrated Booklet Prepaid to Any Address Absolutely Free.

The cost of painting the house and barn, outbuildings and fences is a heavy burden. Cheap paints soon fade, peel or scrape off and white lead and oil costs so much and has to be replaced so often that it is a constant expense to keep the bright, clean appearance so desirable in the cozy cottage home or the elegant mansion. The following are a few of the large users of Carrara Paint:

Pennsylvania R. R. Co.; Pullman Palace Car Co.; Chicago Telephone Co.; Central Union Telephone Co.; Field Museum, Chicago; Kenwood Club, Chicago; Cincinnati Southern; C. & E. I. R. R. Co.; Denver & Rio Grande R. R.; Wellington Hotel, Chicago.

Carrara is used because it lasts longer, never fades, never cracks, never blisters, never peels, covers more surface than the highest priced paints and costs less than the cheap mixed paints that injure instead of protect. There is but one Carrara. It is made by the Carrara Paint Agency, General Offices, 770 Carrara Bldg., Cincinnati, Ohio, and anyone having a house to paint should send for 50 free sample colors and our handsome booklet, showing many buildings reproduced in all the colors just as they are painted from this great paint that has stood the most rigid tests for 25 years and, bear in mind, that it is the only paint ever manufactured that is backed by a positive guarantee in every case. Distributing depots in all principal cities. Write to-day and save half your paint bills in the future.

The Waldorf-Astoria, New York, One of the Most Magnificent Hotels in the World, Has Used Tons and Tons of the World-Famous Carrara Paint.

ELECTRICAL ENGINEERING TAUGHT BY MAIL.

Write for our Free Illustrated Book. "CAN I BECOME AN ELECTRICAL ENGINEER?"

We teach Electrical Engineering, Electric Lighting, Electric Railways, Mechanical Engineering, Steam Engineering, Mechanical Drawing, at your home by mail. Institute indorsed by Thos. A. Edison and others. ELECTRICAL ENGINEER INSTITUTE, Dept. A, 240-242 W. 23d St., New York.

LEARN PROOFREADING.

If you possess a fair education, why not utilize it at a genteel and uncrowded profession paying $15 to $35 weekly? Situations always obtainable. We are the original instructors by mail. HOME CORRESPONDENCE SCHOOL, Philadelphia.

PLATING OUTFIT

$2 Batteries and Harmless Chemicals, with full instructions so that you can do your own plating at home, sent you by mail. Apparatus for Gold Plating, $2.00. Silver or Nickel, $1.50. With gold and Silver and Nickel, $2.00. Circulars Free. Agents Wanted. Electrochemical Works, Dept. 10, 80 John St., New York.

The Typewriter Exchange

1½ Barclay St., NEW YORK
124 La Salle St., CHICAGO
38 Bromfield St., BOSTON
817 Wyandotte St., KANSAS CITY, MO.
209 North 9th St., ST. LOUIS, MO.
536 California St., SAN FRANCISCO, CAL.

We will save you from 10 to 50% on Typewriters of all makes. *Send for Catalogue*

A Handy Book To Have

Montgomery & Co.'s Tool Catalogue

It is illustrated throughout and describes and prices Tools. 704 pages, 6¼ x 4½ ins. The latest edition, with discount sheet by mail for 25 cents. MONTGOMERY & CO., 105 Fulton St., New York City.

Zinc paint cracks; white lead chalks off. **Patton's SUN-PROOF Paint** does neither. Guaranteed to wear for five years.

PITTSBURGH PLATE GLASS Co., General Distributers. Send for Book of Paint Knowledge and Advice (free) to PATTON PAINT CO., 227 Lake St., Milwaukee, Wis.

PURE DELIGHT found in The EDISON **PHONOGRAPH**

Use Edison Moulded Records. Make Records of your own.

The PHONOGRAPH is the only machine that **satisfies** the musical ear. Those who judge the PHONOGRAPH by the old styles, or by other "talking machines," should visit the nearest dealer and hear Mr. Edison's marvelous improvements that produce this perfect result.

PHONOGRAPH Catalogues and Record Lists are Free at all dealers. Five thousand stores sell PHONOGRAPHS. Nine Styles, $10.00 to $100.00. Records 50c.; $5.00 per dozen.

NATIONAL PHONOGRAPH CO., ORANGE, N. J.

New York, 83 Chambers St. Chicago, 144 Wabash Av. San Francisco, 933 Market St. Europe, 32 Rempart Saint Georges, Antwerp, Belgium

50 YEARS' EXPERIENCE

PATENTS

TRADE MARKS DESIGNS COPYRIGHTS &c.

Anyone sending a sketch and description may quickly ascertain our opinion free whether an invention is probably patentable. Communications strictly confidential. Handbook on Patents sent free. Oldest agency for securing patents. Patents taken through Munn & Co. receive *special notice*, without charge, in the

Scientific American.

A handsomely illustrated weekly. Largest circulation of any scientific journal. Terms, $3 a year; four months, $1. Sold by all newsdealers.

MUNN & Co. 361 Broadway, New York

Branch Office, 625 F St., Washington, D. C.

Valves for piston or valve movements of any kind, device for actuating shut-off, C. Nielsen	722,656
Vapor burner, W. Mitchell	722,430
Vehicle alarm, J. M. Justen	722,587
Vehicle body, H. McLoughlin	722,611
Vehicle brake, electric, J. N. Mahoney, reissue	12,098
Vehicle draft attachment, A. P. Speed	722,639
Vehicle fender or safety device, C. E. B. Helbig	722,579
Vehicle, motor, R. Stone	722,262
Vessels' hatchways, cover for, E. W. De Russett	722,215
Violin sound beam, J. Bunch	722,561
Viscosimeter, S. Grand	722,576
Wagon body, J. H. Anderson	722,478
Waist and supporter, S. Vischer	722,472
Wall, J. G. F. Lund	722,257
Washboard, T. W. Woolley	722,394
Water closet seat, C. Sudbrink	722,465
Weather strip, L. A. Bartel	722,352
Windmill starting or stopping mechanism, T. W. Wheeler	722,547
Window, F. Nentwich	722,553
Window insect guard, E. P. Doty	722,499
Window, revolving metallic, P. O. Hultmark	722,305
Window screen, T. D. Ruth	722,653
Wood preserving and creosoting apparatus, L. Hanson	722,505
Wrench, J. A. Boyd	722,483

DESIGNS.

Dish or plate or similar article, A. J. Fondeville	36,243
Game chip, S. A. Cohen	36,242
Metal border, H. Hillbom	36,244

TRADE MARKS.

Antiseptic internal injectors, Kutnow Bros.	39,917
Batteries, carbons, and agglomerates for electrical purposes, Societe Anonyme le Carbone	39,923, 39,924
Beer, lager and bottled, Terre Haute Brewing Co.	39,906
Boots and shoes and leather for same, leather, Regal Shoe Company	39,902
Boots and shoes, leather, J. E. Tilt Shoe Co.	39,900
Boots and shoes, leather, A. Newman & Co.	39,901
Carpet sweepers, Bissell Carpet Sweeper Co.	39,919 to 39,921
Chocolate, Huyler's	39,905
Clocks, electric, H. Reisinger	39,918
Cooking and heating apparatus, certain named, E. H. Huenefeld	39,927
Cream separators, National Dairy Machine Co.	39,922
Damiana compound, Astropathic Institute	39,912
Dyeing and printing textiles, chemical preparations for use in, H. A. Metz & Co.	39,908
Embroidery threads, T. Buettner & Co.	39,899
Gas, gasolene and oil engines, Samson Iron works	39,926
Harness webbing, Russell Manufacturing Co.	39,904
Heating apparatus, Gurney Heater Mfg. Co.	39,925
Homeopathic preparations, Enk Medicine Co.	39,913
Lime, ground white, Rockland-Rockport Lime Co.	39,909
Medicinal preparations, certain named, F. J. Smith	39,914
Paper and envelops, certain named, William Mann Co.	39,898
Remedies, cough, W. Chubbuck	39,915
Remedies for diseases of stock and poultry, Vincent Manufacturing Co.	39,911
Remedies, headache, R. W. Nix	39,916
Rubber boots and shoes, Shawmut Rubber Co.	39,903
Soldering flux, Free-Ko Chemical Co.	39,917
Wines, Morton & Company	39,907

LABELS.

"Black Tiger' Bedbug Destroyer," for insecticides, C. F. R. Medlenka	9,785
"Blue Ribbon Tomato Catsup," for tomato catsup, C. Raab	9,796
"Buffalo Brand," for baking soda, Buffalo Mfg. Co.	9,792
"Christie," for sugar wafers, Importers & Traders Biscuit Co.	9,794
"Christie," for fruit sandwiches, Importers & Traders Biscuit Co.	9,795
"Delorge & Jenning's Tiger Rheumatic Cure," for a medicine, Delorge & Jennings	9,786
"Edam," for cheese wafers, Importers & Traders Biscuit Co.	9,793
"Excelsior Washing Fluid," for washing fluid, C. Raab	9,798
"Golden Crown Tomato Catsup," for tomato catsup, C. Raab	9,797
"Imperial Tycoon Cigars," for cigars, Galvin, La Pretto & Fitzgerald	9,789
"Maltopeptine Gum," for chewing gum, J. W. Morrison, Jr.	9,788
"New England 'Breathe Easy' Asthma Cure," for a medicine, New England Asthma Remedy Co.	9,787
"Ole Bull Pure Rye Whiskey," for whisky, E. C. Armstrong	9,790
"Ralston Cereal Coffee," for cereal coffee, Ralston Purina Co.	9,791

A printed copy of the specification and drawing of any patent in the foregoing list, or any patent in print issued since 1863, will be furnished from this office for 10 cents, provided the name and number of the patent desired and the date be given. Address Munn & Co., 361 Broadway, New York.

Canadian patents may now be obtained by the inventors for any of the inventions named in the foregoing list. For terms and further particulars address Munn & Co., 361 Broadway, New York.

NEW BOOKS, ETC.

GINSENG. By M. G. Kains. New York: Orange Judd Company. 1902. 16mo. Price 50 cents.

Genseng is consumed by the Chinese in enormous quantities. The United States has been one of the chief sources of supply. Within recent years, however, our forests' supply of ginseng has been rapidly decreasing. As a result many attempts have been made to cultivate the plant. The writer has prepared what he considers a practical working manual of the methods which have so far been found most adequate for the growth of the plant. The information presented has been gathered from many trustworthy sources.

LA LANGUE BLEU.—Bolak. Langue Internationale Pratique. Paris: Léon Bollack. 1902. Pp. 89.

EARTHQUAKES. Their Origin and Phenomena. By George Walter Hale.

DEPARTMENT OF THE INTERIOR, UNITED STATES GEOLOGICAL SURVEY. Charles D. Walcott, Director. Preliminary Report on the Ketchikan Mining District, Alaska. With an Introductory Sketch of the Geology of Southeastern Alaska. By Alfred Hulse Brooks. Government Printing Office, Washington. 1902.

THE HARRINGTON AND KING PERFORATING CO.

PERFORATED METALS

OF EVERY DESCRIPTION AND FOR ALL PURPOSES. FOR SCREENS OF ALL KINDS.

Nº 225 NORTH UNION ST CHICAGO, ILL. U.S.A.

This Book is Free

The Mysteries of Hypnotism and Personal Magnetism Revealed

The American College of Sciences, of Philadelphia, Pa., has just published a remarkable book on Hypnotism, Personal Magnetism and Magnetic Healing. It is by far the most wonderful and comprehensive treatise of the kind ever printed. The Directors have decided, for a limited time, to give a free copy to each person sincerely interested in these wonderful sciences. It is the result of the combined effort of twenty of the most famous hypnotic specialists in the world. You can now learn the secrets of Hypnotism and Personal Magnetism at your own home, free.



Hypnotism strengthens your memory and develops a will of iron. It overcomes bashfulness, revives hope, stimulates ambition and determination to succeed and gives you that self-confidence which enables you to convince people of your real worth. It gives you the key to the inner secrets of mind control. It enables you to absolutely control the thoughts and actions of whomsoever you will. When you understand this grand and mysterious science, you can plant suggestions in human minds which will be carried out in a day or even a year hence. You can cure yourself of insomnia, nervousness and business or domestic worry.

You can instantaneously hypnotise people with a mere glance of the eye, without their knowledge, and powerfully influence them to do as you desire. You can develop, to a marvelous degree, any musical or dramatic talent you may have; you can increase your salary; you can develop your telepathic power; you can give thrilling and funny hypnotic entertainments; you can win the everlasting friendship of those you desire; you can protect yourself against the influence of others; you can become a financial success and be recognized as a power in your community.

The American College guarantees to teach you the secret of attaining all these things. It is the largest and most successful school of Hypnotism in the world. It is chartered by the State laws, and carries out every promise faithfully. If you want a copy of its free book, just send your name and address, no money, to the American College of Sciences, Dept. S H 14, 420 Walnut Street, Philadelphia, Pa., and you will receive it by return mail, postpaid.

I PRINT MY OWN CARDS

Circulars, newspaper. Press, $5. Larger size, $18.00. Money saver. Big profits printing for others. Type setting easy, rules sent. Write for catalog, presses, type, paper, etc., to factory. The Press Co., Meriden, Conn.

20TH CENTURY CUT **RÉMOH DIAMONDS**

1 Carat 20th Century Cut Remoh Diamond Ring or Stud, Solid-Gold mountings, each $3.00 or both at $5.00. Sent by registered mail upon receipt of price. THE FINEST IMITATIONS ON EARTH. Our magnificent catalog fully describing them and explaining how to order, mailed to any address upon request FREE

NO AGENTS WANTED.

RÉMOH JEWELRY COMPANY, 834 OLIVE STREET, ST. LOUIS, MO.

SHOE BLACKING.—FORMULAS FOR liquid and solid blacking are given in SUPPLEMENT Nos. 1213 and 1239. Price 10 cents each. For sale by Munn & Co. and all newsdealers

A UNIVERSAL POCKET MEASURE

The only practical all around measure ever made. Measures curves of all kinds as easily as straight work. Simpler than a rule for it is a *revolving rule*. A time, brain and money saver. Absolutely accurate. Measures any distance. Can be set at "zero" at will. Any one can use it. Highest endorsements. Send for free detailed description.

STECKENREITER MFG. CO., 99 LAKE STREET, CHICAGO.

AN ENGINEER'S LIBRARY.

An absolute Encyclopedia for Engineers or for Steam Users, Electricians, Firemen and Machinists, is the **HANDBOOK ON ENGINEERING.** By HENRY C. TULLEY.

Third edition, enlarged and revised, 5,000 copies now ready. Sent anywhere on receipt of price, $3.50—money back if dissatisfied. 900 pages. 400 fine illustrations. Thoroughly reliable and practical. Handsomely bound in leather and gilt. Pocket-book form.

H. C. TULLEY & CO., 1000 Wainwright Bldg., St. Louis, Mo., U. S. A.

OIL--SMELTER--MINES

Dividend-Paying Mining, Oil and Smelter Stocks, Listed and Unlisted, our Specialty.

DOUGLAS, LACEY & CO.

Bankers & Brokers, Fiscal Agents. Members N. Y. Consolidated Stock Exchange. 66 BROADWAY & 17 NEW ST., NEW YORK.

Booklets giving our successful plan for realizing the large interest and profits of legitimate mining, oil and smelter investments, sub. blanks, full particulars, etc., sent free on application.

MODEL AND EXPERIMENTAL WORK.

Electrical and Mechanical Instruments. Small Mach'y. EDWARD KLEINSCHMIDT, 62 W. Broadway, New York.

SPECIAL MANUFACTURING. SPEC MACHINERY MODELS EXPERIMENTAL WORK. DIES AND STAMPING. PROMPT. GLOBE MACH & STAMPING CO. 970 HAMILTON ST CLEVELAND, O.

IF YOU WANT to BUY or SELL Real Estate or Business write me. I can sell your property quickly for Cash no matter where located. Write to-day and learn how. FRANK P. CLEVELAND, Real Estate Expert, 1507 Adams Express Bldg., Chicago.

"THIS BEATS NEW JERSEY."

Charters procured under South Dakota laws for a few dollars. Write for Corporation laws, blanks, by-laws and forms to PHILIP LAWRENCE, late Ass't Sec. of State, Huron, S. Dak. or Room K, 30th floor, 220 B'way, N. Y.

Mathematicians Wanted

The profession of actuaryship offers a splendid field for those possessing mathematical ability, as positions command $4,000 a year and over. Our course is prepared by leading actuaries and is under their supervision. Address

HOME CORRESPONDENCE SCHOOL, 416 Walnut St., Philadelphia, Pa.

INVENTIONS DEVELOPED.

WALTER E. FREEMAN, M.E.

Special machinery, electrical and chemical apparatus made on short notice. Good accommodations for inventors. 405 E. 23d St., New York.

FREE Catalogue of Architectural, Scientific and Technical Books. Prospectus for 1903 for "Architects' and Builders' Magazine," monthly $2 a year. WM. T. COMSTOCK, Pub., 23 Warren St., New York.

TYPE WHEELS, MODELS & EXPERIMENTAL WORK, SMALL MACHINERY, NOVELTIES & ETC. NEW YORK STENCIL WORKS 100 NASSAU ST. N.Y.

Are you interested in Patents, Model or Experimental work? Our booklet entitled **WHAT WE DO—HOW WE DO IT** will be sent to you on request. KNICKERBOCKER MACHINE WORKS, Inc., 8-10-12 Jones Street, New York.

ICE MACHINES, Corliss Engines, Brewers' and Bottlers' Machinery. THE VILTER MFG. CO., 899 Clinton Street, Milwaukee Wis.

MODELS & GEARS CATALOGUE FREE UNION MODEL WORKS 181 CLARK, CHICAGO

MODELS & EXPERIMENTAL WORK. Inventions developed. Special Machinery. E. V. BAILLARD, Fox Bldg., Franklin Square, New York.

I will Ship to any Station in the United States for THE CELEBRATED **WILLARD STEEL RANGE** $25.00

It has six 8-inch lids; 15-gallon reservoir; large warming closet; oven 21 ins. deep, 17 ins. wide, 12 ins. high; top cooking surface, 30x36 ins.; lined throughout with Asbestos; Duplex grate; burns wood or coal. Guaranteed in every respect; weighs 400 lbs. Write for free descriptive circular and testimonials. AGENTS WANTED.

WM. G. WILLARD, Dept. 112, 619-21 N. 4th Street, St. Louis, Mo.

THOROUGH INSPECTIONS

HARTFORD STEAM BOILER INSPECTION AND INSURANCE CO. HARTFORD, CONN.

AND INSURANCE AGAINST LOSS OR DAMAGE TO PROPERTY AND LOSS OF LIFE AND INJURY TO PERSONS CAUSED BY

STEAM BOILER EXPLOSIONS

J. M. ALLEN, President · J. B. PIERCE, Secretary · THEO. M. ALVORD, Treasurer · W. B. FRANKLIN, Vice President · J. B. ALLEN, 2d Vice President · J. F. MIDDLEBROOK, Asst. Sec'y

Railroad Locomotives Stop

every 125 miles for coal and every 90 miles for water, but the 1903 Model 20 Horse Power

Winton Touring Car

travels 175 miles with one filling of gasoline and lubricating oil. With the improved cooling system the only loss of water is by natural evaporation. Write for catalogue.

The Winton Motor Carriage Co., Cleveland, Ohio.

DIAMOND DETACHABLE TIRES

WE ISSUE every once in a while, a letter, a booklet, a folder or a catalogue, wherein is shown information relating to Automobile Tires, that may be of some value to you.

It costs the price of a postal card to have your name added to our mailing list.

THE DIAMOND RUBBER CO., Akron, Ohio.

WHEEL CHAIRS
WE MAKE OVER 70 STYLES

and are fully equipped to make any special designs or size.

Catalogue "B" illustrates and describes (free).

Reclining and Library Chairs, over 30 styles.

Catalogue "C" (free).

GEO. F. SARGENT CO., 391 Fourth Ave., New York.

A Box of Fifty Two-for-a-Quarter Havana Cigars ABSOLUTELY FREE

to a very limited number of smokers in every community. We use this method to advertise our goods instead of taking large and expensive space in magazines. If you like a good cigar don't delay but write at once for full particulars.

Evans Cigar Co., 9 Lexington St., Chicago

CHARTER ENGINE

USED ANY PLACE BY ANY ONE FOR ANY PURPOSE

Stationaries, Portables, Sawing Outfits, Hoisters, Engines and Pumps.

FUEL—Gasoline, Gas, Distillate.

Send for Illustrated Catalogue and Testimonials, and State Your Power Needs.

CHARTER GAS ENGINE CO., Box 148, STERLING, ILL.

Magnolia Metal Co.'s Stock

7% Preferred Stock FIRST LIEN

Selling at Par,

$100 A SHARE

A limited amount offered for public subscription. Dividends paid semi-annually—April 1st and October 1st. Magnolia Metal is famous the world over and we have offices and factories in principal cities.

Checks, if desired, can be sent to the Merchants Exchange National Bank of New York City, or Federal National Bank of Pittsburg, Pa.

Write to us for chartered accountant's report, and prospectus.

MAGNOLIA METAL CO., SECURITY OFFICES 511-513 W. 13th St., New York.

RIVETT LATHE

No up-to-date manufacturer can afford to do without it.

HIGHEST AWARD wherever exhibited. Send for Catalog.

Fanguil Watch Tool Company, BRIGHTON, BOSTON, MASS., U. S. A.

Waltham Watches

The name is a guarantee.

"The Perfected American Watch," an illustrated book of interesting information about watches, will be sent free upon request.

American Waltham Watch Company, Waltham, Mass.

JESSOP STEEL CO
MFR. OF CRUCIBLE SHEET STEEL
WASHINGTON, PA.

The "Stanhope Motorette"

is a 6½ h. p., Single Cylinder, De Dion type of motor, weighing 900 pounds and 1,000 when loaded with water and gasoline. Two speeds forward and reverse. Motor easily accessible, simple in operation and economical, simply, but durably constructed and highly finished throughout. For illustrated booklet and fuller particulars address

THE GEORGE N. PIERCE CO., BUFFALO, N. Y.

POWER AIR PUMP FOR STEAM CARRIAGES

ADDRESS MALTBY No. 11 CLINTON ST. BROOKLYN, N.Y.

Computing Figures

mentally is probably the hardest kind of toil known. The Comptometer makes it easy, is twice as quick, insures accuracy and relieves all mental and nervous strain. Why don't you get one?

Write for Pamphlet.

FELT & TARRANT MFG. CO. 52-56 ILLINOIS ST., CHICAGO.

Watchman's Register with Time Lock

Sanford's Improved Register is the best in the world. Information and prices on application to

C. E. SANFORD, 18 Broadway, New York. Inventor, Proprietor and Sole Manufacturer.

SPLITDORF SPARK COILS

25 VANDEWATER ST. N.Y.

Columbia

Light Electric Runabout

MARK XXXVIII



Fastest, handsomest and most convenient Electric Runabout on the market. Five speeds up to 15 miles per hour. Underslung battery and motor, leaving body space entirely free for luggage.

Catalogue illustrating and describing 20 different Columbia models will be sent on request.

Electric Vehicle Company, Hartford, Conn.

NEW YORK Salesroom—134, 136, 138 West 39th Street.
BOSTON—43 Columbus Avenue.
CHICAGO—1421 Michigan Avenue.

Don't Experiment

BUY

FISK TIRES

FISK RUBBER COMPANY, Chicopee Falls, Mass.

PALATABLE WATER-STILL

Produces an absolutely pure and aerated water for manufacturing or drinking purposes.

Attachable to any steam boiler.

Made in all sizes, from 10 to 200 gallons distilled water per hour.

In use in U. S. Army and Hospital Marine service.

Write for catalogue.

PALATABLE WATER-STILL COMPANY, Boston, Mass., U. S. A.

PARALLEL CHESLY & Co CLAMPS ALL ANGLES SIDES Chicago U.S.A.

NEW ENGLAND WATCHES

The PADISHAH

The best low priced watch in the world. Sold in every country on the globe for the one price or its equivalent. . . . .

$2.00 EACH

Plain or fancy colored Sporting Dials.

We make all styles and sizes of watches for men and women. . . . . Catalogues sent on request.

NEW ENGLAND WATCH CO., Factories: Waterbury, Conn.

Offices: New York, 37 & 39 Maiden Lane. Chicago, 131 to 137 Wabash Avenue. San Francisco, Spreckels Building.

Take the Short Cut

GO RIGHT TO CARRIAGE HEADQUARTERS

Write to-day for our illustrated catalogue (free) which describes our goods truthfully, explains our method and our guarantee and makes it safe, simple and easy for you to get carriages, harness and horse accessories direct from our factory at wholesale prices.

THE COLUMBUS CARRIAGE and HARNESS COMPANY.

Factory and General Office, Columbus, O. Western Office & Distributing House, St. Louis, Mo.

Write to nearest office.

COLD GALVANIZING.

AMERICAN PROCESS. NO ROYALTIES

SAMPLES AND INFORMATION ON APPLICATION.



NICKEL AND Electro-Plating

Apparatus and Material

THE Hanson & VanWinkle Co., Newark, N. J. 136 Liberty St., N. Y. 30 & 32 S. Canal St. Chicago.

It won't cost you a cent to test "Royal Worcester" Belting.

We will send sample belt for testing on your own machinery, absolutely free of cost to you. Puts you under no obligation whatever to buy unless you decide for yourself that it is the best and most economical belt for you to use.

REMEMBER: Royal Worcester Belts—choicest selection of hides tanned old-fashioned, pure oak process, cut not over 18 inches from center, not more than 54 inches long. Guaranteed not to stretch, sag, or give trouble.

GRATON & KNIGHT MFG. CO.

Oak Leather Belt Makers, Worcester, Mass.



If you want most for your money insist on PRESIDENT being stamped in the buckle when you buy SUSPENDERS

Fifty cents and a dollar. Ask at favorite shop.

or post prepaid from C. A. Edgarton Mfg. Co., Box 222 J, Shirley, Mass.

Send 6 cents for catalogue.

The Back

Orient Motor Car

8 H. P. PRICE $950

All speeds to 30 miles per hour. Will climb any grade. Write for descriptive catalogues.

WALTHAM MFG. CO., - Waltham, Mass.

WARWICK MOTOR CYCLE

Weight 98½ lbs.

SPEED, 45 MILES PER HOUR.

The best Hill Climber made.

Write for catalogue which gives particulars of Motor Cycles and Automobiles.

Warwick Cycle & Automobile Co., Springfield, Mass.

Scales All varieties at lowest prices. Best Railroad Track and Wagon or Stock Scales made. Also 1000 useful articles, including Safes, Sewing Machines, Bicycles, Tools, etc. Save Money. Lists Free. CHICAGO SCALE CO., Chicago, Ill

Beauty and Utility

Every business man knows the annoyance of loose shirt cuffs. Every wise business man ought to know that they can be easily fixed and regulated to any desired length below the coat sleeve by using

Washburne's Cuff Holders



They can be instantly attached or detached. They never come loose—have a grip like a bulldog.

Illustrated catalogue on request.

Sample pair of Cuff Holders sent by mail on receipt of 20c.

AMERICAN RING CO., Box 8, Waterbury, Conn.